

FIELD MAINTENANCE PRINT SET

TABLE OF CONTENTS

B-TC-VT100-0-1	VT100 UNIT ASSY. (TC)
E-UA-VT100-0-0	VT100 UNIT ASSY.
C-PL-VT100-0-0	VT100 UNIT ASSY. (PL)
E-UA-5413009-0-0	BASIC VIDEO BOARD
K-PL-5413009-0-DBP	BASIC VIDEO BOARD (PL)
D-CS-5413009-0-1	BASIC VIDEO BOARD (CS)
E-UA-5412996-0-0	H7831 POWER SUPPLY BOARD
K-PL-5412996-0-DBP	H7831 POWER SUPPLY BOARD (PL)
D-CS-5412996-0-1	H7831 POWER SUPPLY BOARD (CS)
D-AD-7014979-0-0	POWER SUPPLY ASSY.
E-UA-5413404-0-0	KEYBOARD ASSY.
K-PL-5413404-0-DBP	KEYBOARD ASSY. (PL)
D-CS-5413404-0-1	KEYBOARD ASSY. (CS)
D-AD-7015765-0-0	KEYBOARD/KEYCAP ASSY.
C-PL-7015765-0-0	KEYBOARD/KEYCAP ASSY. (PL)
D-AR-7015765-0-1	KEYCAP ARRANGEMENT (MAIN ARRAY & NUMERIC)
D-IA-7014978-0-0	POWER CABLE ASSY.
D-CS-3014590-0-1	CRT MONITOR (CS) (FOR PS-3014590-0-0)
E-UA-VT1XX-AA-0	20 MA CURRENT LOOP OPTION
E-UA-5413206-0-0	20 MA CURRENT LOOP
K-PL-5413206-0-DBP	20 MA CURRENT LOOP (PL)
D-CS-5413206-0-1	20MA CURRENT LOOP (CS)
D-IA-7015273-0-0	20 MA ADAPTER ASSY.
C-IA-7015506-0-0	CABLE, INTERNAL
C-UA-BC05F-0-0	CABLE INTERFACE BC05F
E-UA-5413097-0-0	ADVANCED VIDEO BOARD
K-PL-5413097-0-DBP	ADVANCED VIDEO BOARD (PL)
D-CS-5413097-0-1	ADVANCED VIDEO BOARD (CS)
A-PL-VT100-0	SHIPPING LIST VT100
A-SP-VT100-W-0	WORD PROCESSING TERMINAL INSTALLATION NOTES
D-UA-5414131-0-0	VT100 MONITOR
K-PL-5414131-0-DBP	VT100 MONITOR
D-CS-5414131-0-1	VT100 MONITOR

UNIT VARIATIONS COVERED BY THIS PRINT SET
VT100-AA
VT100-AB
VT100-NA
VT100-NB
VT100-WA
VT100-WB
VT100-WC
VT100-WD
VT100-WE
VT100-WF
VT100-WG
VT100-WH
VT100-WJ
VT100-WK
VT100-WY
VT100-WZ
VT100-LA
VT100-LB
VT100-PA
VT100-PB
VT100-PC
VT100-PD
VT100-PE
VT100-PF
VT100-BA
VT100-BB
VT100-CA
VT100-CB
VT100-DA
VT100-DB


VT100-0


Field Maintenance Print Set

Digital Equipment Corporation

PRINT SET ORDER NO. MP00633

REVISIONS	REV	CHG. NO.	DATE	USED ON OPTION/MODEL	DRN.	DATE	TITLE: VT100 UNIT ASSY. (TABLE OF CONTENTS)							
					B. BLODGETT	27 OCT 77								
					CHK'D	DATE								
					D. HEALY	10 APR 78	PROJ. ENG.	DATE	SIZE	CODE	NUMBER	REV.		
					G. DOUMANI	6-26-78	G. DOUMANI	6-26-78	B	TC	VT100-0-1	E		
					FIELD SERV.	DATE	DIST.							
					J. ZALESKA	12 JUL 78								
				SHEET 1 OF 1										





DESCRIPTION		QTY	UNIT	ITEM NO.
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES				
QUANTITY	DESCRIPTION	QTY	UNIT	ITEM NO.
1	VT100 UNIT ASSY	1	UNIT	1
1	VT100-2-0-AJ	1	UNIT	2
1	VT100-2-0-AJ	1	UNIT	3
1	VT100-2-0-AJ	1	UNIT	4
1	VT100-2-0-AJ	1	UNIT	5
1	VT100-2-0-AJ	1	UNIT	6
1	VT100-2-0-AJ	1	UNIT	7
1	VT100-2-0-AJ	1	UNIT	8
1	VT100-2-0-AJ	1	UNIT	9
1	VT100-2-0-AJ	1	UNIT	10
1	VT100-2-0-AJ	1	UNIT	11
1	VT100-2-0-AJ	1	UNIT	12
1	VT100-2-0-AJ	1	UNIT	13
1	VT100-2-0-AJ	1	UNIT	14
1	VT100-2-0-AJ	1	UNIT	15
1	VT100-2-0-AJ	1	UNIT	16
1	VT100-2-0-AJ	1	UNIT	17
1	VT100-2-0-AJ	1	UNIT	18
1	VT100-2-0-AJ	1	UNIT	19
1	VT100-2-0-AJ	1	UNIT	20
1	VT100-2-0-AJ	1	UNIT	21
1	VT100-2-0-AJ	1	UNIT	22
1	VT100-2-0-AJ	1	UNIT	23
1	VT100-2-0-AJ	1	UNIT	24
1	VT100-2-0-AJ	1	UNIT	25
1	VT100-2-0-AJ	1	UNIT	26
1	VT100-2-0-AJ	1	UNIT	27
1	VT100-2-0-AJ	1	UNIT	28
1	VT100-2-0-AJ	1	UNIT	29
1	VT100-2-0-AJ	1	UNIT	30
1	VT100-2-0-AJ	1	UNIT	31
1	VT100-2-0-AJ	1	UNIT	32
1	VT100-2-0-AJ	1	UNIT	33
1	VT100-2-0-AJ	1	UNIT	34
1	VT100-2-0-AJ	1	UNIT	35
1	VT100-2-0-AJ	1	UNIT	36
1	VT100-2-0-AJ	1	UNIT	37
1	VT100-2-0-AJ	1	UNIT	38
1	VT100-2-0-AJ	1	UNIT	39
1	VT100-2-0-AJ	1	UNIT	40
1	VT100-2-0-AJ	1	UNIT	41
1	VT100-2-0-AJ	1	UNIT	42
1	VT100-2-0-AJ	1	UNIT	43
1	VT100-2-0-AJ	1	UNIT	44
1	VT100-2-0-AJ	1	UNIT	45
1	VT100-2-0-AJ	1	UNIT	46
1	VT100-2-0-AJ	1	UNIT	47
1	VT100-2-0-AJ	1	UNIT	48
1	VT100-2-0-AJ	1	UNIT	49
1	VT100-2-0-AJ	1	UNIT	50
1	VT100-2-0-AJ	1	UNIT	51
1	VT100-2-0-AJ	1	UNIT	52
1	VT100-2-0-AJ	1	UNIT	53
1	VT100-2-0-AJ	1	UNIT	54
1	VT100-2-0-AJ	1	UNIT	55
1	VT100-2-0-AJ	1	UNIT	56
1	VT100-2-0-AJ	1	UNIT	57
1	VT100-2-0-AJ	1	UNIT	58
1	VT100-2-0-AJ	1	UNIT	59
1	VT100-2-0-AJ	1	UNIT	60
1	VT100-2-0-AJ	1	UNIT	61
1	VT100-2-0-AJ	1	UNIT	62
1	VT100-2-0-AJ	1	UNIT	63
1	VT100-2-0-AJ	1	UNIT	64
1	VT100-2-0-AJ	1	UNIT	65
1	VT100-2-0-AJ	1	UNIT	66
1	VT100-2-0-AJ	1	UNIT	67
1	VT100-2-0-AJ	1	UNIT	68
1	VT100-2-0-AJ	1	UNIT	69
1	VT100-2-0-AJ	1	UNIT	70
1	VT100-2-0-AJ	1	UNIT	71
1	VT100-2-0-AJ	1	UNIT	72
1	VT100-2-0-AJ	1	UNIT	73
1	VT100-2-0-AJ	1	UNIT	74
1	VT100-2-0-AJ	1	UNIT	75
1	VT100-2-0-AJ	1	UNIT	76
1	VT100-2-0-AJ	1	UNIT	77
1	VT100-2-0-AJ	1	UNIT	78
1	VT100-2-0-AJ	1	UNIT	79
1	VT100-2-0-AJ	1	UNIT	80
1	VT100-2-0-AJ	1	UNIT	81
1	VT100-2-0-AJ	1	UNIT	82
1	VT100-2-0-AJ	1	UNIT	83
1	VT100-2-0-AJ	1	UNIT	84
1	VT100-2-0-AJ	1	UNIT	85
1	VT100-2-0-AJ	1	UNIT	86
1	VT100-2-0-AJ	1	UNIT	87
1	VT100-2-0-AJ	1	UNIT	88
1	VT100-2-0-AJ	1	UNIT	89
1	VT100-2-0-AJ	1	UNIT	90
1	VT100-2-0-AJ	1	UNIT	91
1	VT100-2-0-AJ	1	UNIT	92
1	VT100-2-0-AJ	1	UNIT	93
1	VT100-2-0-AJ	1	UNIT	94
1	VT100-2-0-AJ	1	UNIT	95
1	VT100-2-0-AJ	1	UNIT	96
1	VT100-2-0-AJ	1	UNIT	97
1	VT100-2-0-AJ	1	UNIT	98
1	VT100-2-0-AJ	1	UNIT	99
1	VT100-2-0-AJ	1	UNIT	100

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION											
					AA	AB	NA	NB	WA	WB	WC	WD	WE	WF	WG	WH
1	1	D-UA-7014653-0-0	7014653-00	KEYBOARD ASSY	1	1	-	-	-	-	-	-	-	-	-	-
2	2	E-IA-7014980-0-0	7014980-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
3	3	D-IA-7014976-0-0	7014976-00	WORT BOX ASSY	1	1	1	1	1	1	1	1	1	1	1	1
4	4	D-IA-7014974-0-0	7014974-00	ENCLOSURE, CRT TOP ASSY	1	1	1	1	1	1	1	1	1	1	1	1
5	5		7014975-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
6	6		7014977-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
7	7	D-AD-7014979-0-0	7014979-00	POWER SUPPLY ASSY	1	1	1	1	1	1	1	1	1	1	1	1
8	8		7014978-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
9	9		5413009-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
10	10		7419836-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
11	11		3016080-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
12	12		9010007-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
13	13		9009967-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
14	14		3615680-00	LABEL,ADHESIVE BACK,SWITCH POSIT	1	1	1	1	1	1	1	1	1	1	1	1
15	15	A-PS-1700083-0-0	1700083-09	PWR CORD,TERM. 75IN,18-3,125V 10	1	-	1	-	1	-	1	-	1	-	1	-
16	16	A-PS-1700083-0-0	1700083-10	PWR CORD,TERM. 75IN,18-3,250V 6	-	1	-	1	-	1	-	1	-	1	-	1
17	17	D-UA-7014653-0-0	7014653-02	KEYBOARD ASSY.	-	-	1	1	-	-	-	-	-	-	-	-
18	18		7414213-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
19	19		3613210-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
20	20		3613210-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
21	21		3613211-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
22	22		3700324-00	INSTR PKG DISPLAY VT100	1	1	1	1	1	1	1	1	1	1	1	1
23	23	E-UA-VT1XX-AA-0	VT1XX-AA	VT100 20MA CURRENT LOOP OPTION W	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF
24	24	A-PL-VT1XX-AB-0	VT1XX-AB	ADVANCED VIDEO OPTION FOR VT100	REF	REF	REF	REF	REF	REF	-	-	-	-	-	-
25	25		9006659-00	WASHER,FLAT STEEL	1	1	1	1	1	1	1	1	1	1	1	1
26	26		9007649-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
27	27		9010112-00	SCREW,WASH HEX SLOT THD RL 6-	1	1	1	1	1	1	1	1	1	1	1	1
28	28	E-UA-7014653-0-0	7014653-03	KEYBOARD ASSY.	-	-	-	-	1	1	-	-	-	-	-	-
29	29		5413097-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
30	30		9009313-01	SUPPORT,C.BD.,FLAME RET.,NATURAL	-	-	-	-	4	4	4	4	4	4	4	4

REVISION HISTORY			BASIC PART NO: VT100		DRN: B. BLODGETT		DATE: 3-SEP-77		D I G I T A L							
ENG	ECO NUMBER	REV	SECTION A OF C						TITLE PARTS LIST							
JD	VT100-ML040	Z	SECTION. VARIATION INDEX		CHK'D: D. HEALY		DATE: 24-SEP-77		VT100 UNIT ASSY.							
GB	VT100-ML042	AA	[A] AA,AB,NA,NB,WA,WB,													
GB	VT100-ML043	AB	WC,WD,WE,WF,WG,WH													
GB	VT100-ML044	AC	[B] WJ,WK,WY,WZ,LA,LB,		DES.ENG.: E. WEDEKING		DATE: 26-JUN-78									
GB	VT100-ML045	AD	PA,PB,PC,PD,PE,PF													
GB	VT100-ML046	AE	[C] BA,BB,CA,CB,DA,DB						DOCUMENT NUMBER							
GB	VT100-ML047	AF			RESP.ENG.: G. DOUMANI		DATE: 26-JUN-78									
AJ	VT100-ML048	AH	[D]						SIZE CODE NUMBER REV							
GB	VT100-ML049	AJ			MFG.ENG.: K. HOFFMAN		DATE: 7-JUL-78		K PL VT100-0-DBP AJ							
			[E]													
			[F]													
					ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:		FILE NAME: EDIT #							
					E-UA-VT100-0-0		B-DD-VT100-0		MLOBAJ.PLS 19							

*THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.

COPYRIGHT (C) 1982. DIGITAL EQUIPMENT CORPORATION *

AUTOMATED BY PRTLST.3P(44)

P A R T S L I S T

SHEET A2 OF A3

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION											
					AA	AB	NA	NB	WA	WB	WC	WD	WE	WF	WG	WH
31	31		9010135-00	SCREW,TAP HEXWW SLOT THD RL 8-	4	4	4	4	4	4	4	4	4	4	4	4
32	32	E-UA-7014653-0-0	7014653-05	KEYBD ASSY FR CANADIAN WP KEYCAP	-	-	-	-	-	-	1	1	-	-	-	-
33	33	E-UA-7014653-0-0	7014653-06	KEYBD ASSY FRENCH + WP KEYCAPS	-	-	-	-	-	-	-	-	1	1	-	-
34	34	E-UA-7014653-0-0	7014653-07	KEYBD ASSY DUTCH WP KEYCAPS	-	-	-	-	-	-	-	-	-	-	1	1
35	35	E-UA-7014653-0-0	7014653-08	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
36	36	D-UA-5413097-0-0	5413097-03	VT100 ADVANCED VIDEO	-	-	-	-	-	-	1	1	1	1	1	1
37	37		5413009-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
38	38		3016080-53	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
39	39	D-IA-7014974-0-0	7014974-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
40	40	D-UA-7014653-0-0	7014653-10	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
41	41	D-UA-7014653-0-0	7014653-09	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
42	42		3616157-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
43	43	B-IA-7423018-0-0	7423018-00	ISOLATION MOUNT.	2	2	2	2	2	2	2	2	2	2	2	2
44	44	B-MD-7423006-0-0	7423006-00	SCREW,HEX WASHER HD,4-40	2	2	2	2	2	2	2	2	2	2	2	2
45	45		9008193-00	WASHER,FLAT NYLON	2	2	2	2	2	2	2	2	2	2	2	2
46	46		7016624-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
47	47	D-IA-7419469-0-0	7419469-00	STOP P.C. CARD	1	1	1	1	1	1	1	1	1	1	1	1
48	48		1212405-00	CARD GUIDE,NYLON	2	2	2	2	2	2	2	2	2	2	2	2
49	49	A-PS-3617544-0-0	3617544-00	LABEL,X-RAY RADIATION	1	1	1	1	1	1	1	1	1	1	1	1
50	50	SEE NOTE	3617674-01	LABEL,SERIAL & POWER W/UL & CSA	1	1	1	1	1	1	1	1	1	1	1	1
51	51		9010234-00	CLIP,CONN MTG. ZINCP	4	4	4	4	4	4	4	4	4	4	4	4
52	52	E-UA-5413097-0-0	5413097-01	ADVANCE VIDEO LA120	-	-	-	-	1	1	-	-	-	-	-	-
53	53	E-IA-7017434-0-DBU	7017434-00	CHASSIS WELDMENT	1	1	1	1	1	1	1	1	1	1	1	1
54	54		1217594-00	STANDOFF,PC BOARD MOUNTED	4	4	4	4	4	4	4	4	4	4	4	4
55	55		9009964-00	PLUNGER, 5/16 DIA	4	4	4	4	4	4	4	4	4	4	4	4
56	56		9009966-01	GROMMET,SNAP-IN POLYCARBONAT	4	4	4	4	4	4	4	4	4	4	4	4
57	57		9009624-00	BUMPER,SQUARE ADH BACK RUBBER	1	1	1	1	1	1	1	1	1	1	1	1
58	58		1218041-00	BUMPER, W/STEM SBR	1	1	1	1	1	1	1	1	1	1	1	1
59	59		9009636-00	CLAMP, CABLE, FOR FLAT CABLE	3	3	3	3	3	3	3	3	3	3	3	3
60	60	E-MD-7423954-0-DBU	7423954-00	CARD CAGE	1	1	1	1	1	1	1	1	1	1	1	1
61	61	D-UA-5413009-0-0	5413009-03	VT100 BASIC VIDEO	1	1	1	1	1	1	-	-	-	-	-	-
62	62	D-IA-7014978-0-0	7014978-03	DC POWER CABLE VT100 FCC	1	1	1	1	1	1	1	1	1	1	1	1
63	63		3617880-03	LABEL,FCC CLASS A PERIPHERAL	1	1	1	1	1	1	1	1	1	1	1	1
64	64	B-IA-7017970-0-0	7017970-YA	CABLE GROUNDING 3.5	1	1	1	1	1	1	1	1	1	1	1	1
65	65	D-UA-5413009-0-0	5413009-05	VT100 BASIC VIDEO	-	-	-	-	-	-	1	1	1	1	1	1
66	66		9000049-08	SCREW,SEMS HEX SLOT 6-	12	12	12	12	12	12	12	12	12	12	12	12
67	67	SEE NOTE	3700324-01	PKG DISPLAY VT100	REF	REF	REF	REF	-	-	-	-	-	-	-	-
68	68	SEE NOTE	3700520-00	PKG, H9780-BA CAB	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF
69	69	E-IA-7014980-0-0	7014980-04	BASE, ENCLOSURE ASSY	1	1	1	1	1	1	1	1	1	1	1	1
70	70	D-AD-7018349-0-0	7018349-01	MONITOR ASSY, CRT, DIRECT DRIVE	1	1	1	1	1	1	1	1	1	1	1	1
71	71	D-AD-7018349-0-0	7018349-05	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
72	72	E-UA-VT100-0-0	VT100-AA	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
73	73	E-UA-VT100-0-0	VT100-AB	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
74	74		3617905-01	LABEL,WARNING 120V 60HZ	1	-	1	-	1	-	1	-	1	-	1	-
75	75		3617905-02	LABEL,WARNING 220-240V50HZ	-	1	-	1	-	1	-	1	-	1	-	1

! D ! I ! G ! I ! T ! A ! L !	! TITLE	! SECTION A OF C	! SIZE ! CODE !	! DOCUMENT NUMBER	! REV !
! ! ! ! ! ! ! !	VT100 UNIT ASSY.	! ! ! ! ! ! ! !	! K ! FL !	VT100-0-DBP	AJ

AUTOMATED BY PRTLST.3P(44)

PARTS LIST

SHEET A3 OF A3

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION	AA	AB	NA	NB	WA	WB	WC	WD	WE	WF	WG	WH
------	------	-----------------	-------------	-------------	------------------------	----	----	----	----	----	----	----	----	----	----	----	----

76 NOTE: ALTERNATE SHIPPING CONTAINERS FOR USE WITH VARIATIONS AS INDICATED
77 NOTE: (LABEL, SERIAL NUMBER) 3617674-08 MAYBE USED AS ALTERNATE PART NUMBER TO ITEM #50 (3617674-01)

D	I	G	I	T	A	L	TITLE	VT100 UNIT ASSY.	SECTION A	OF C	SIZE	CODE	DOCUMENT NUMBER	REV
											K	PL	VT100-3-DBF	AJ

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION											
					WJ	WK	WY	WZ	LA	LB	PA	PB	PC	PD	PE	PF
1	1	D-UA-7014653-0-0	7014653-00	KEYBOARD ASSY	-	-	-	-	1	1	-	-	-	-	-	-
2	2	E-IA-7014980-0-0	7014980-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
3	3	D-IA-7014976-0-0	7014976-00	WORT BOX ASSY	1	1	1	1	1	1	1	1	1	1	1	1
4	4	D-IA-7014974-0-0	7014974-00	ENCLOSURE, CRT TOP ASSY	1	1	1	1	1	1	-	-	-	-	-	-
5	5		7014975-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
6	6		7014977-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
7	7	D-AD-7014979-0-0	7014979-00	POWER SUPPLY ASSY	1	1	1	1	1	1	1	1	1	1	1	1
8	8		7014978-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
9	9		5413009-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
10	10		7419836-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
11	11		3016080-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
12	12		9010007-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
13	13		9009967-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
14	14		3615680-00	LABEL,ADHESIVE BACK,SWITCH POSIT	1	1	1	1	1	1	1	1	1	1	1	1
15	15	A-PS-1700083-0-0	1700083-09	PWR CORD,TERM. 75IN,18-3,125V 10	1	-	1	-	1	-	1	-	1	-	1	-
16	16	A-PS-1700083-0-0	1700083-10	PWR CORD,TERM. 75IN,18-3,250V 6	-	1	-	1	-	1	-	1	-	1	-	1
17	17	D-UA-7014653-0-0	7014653-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
18	18		7414213-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
19	19		3613210-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
20	20		3613210-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
21	21		3613211-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
22	22		3700324-00	INSTR PKG DISPLAY VT100	1	1	1	1	1	1	1	1	1	1	1	1
23	23	E-UA-VT1XX-AA-0	VT1XX-AA	VT100 20MA CURRENT LOOP OPTION W	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF
24	24	A-PL-VT1XX-AB-0	VT1XX-AB	ADVANCED VIDEO OPTION FOR VT100	-	-	-	-	REF	REF	REF	REF	REF	REF	REF	REF
25	25		9006659-00	WASHER,FLAT STEEL	1	1	1	1	1	1	1	1	1	1	1	1
26	26		9007649-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
27	27		9010112-00	SCREW,WASH HEX SLOT THD RL 6-	1	1	1	1	1	1	1	1	1	1	1	1
28	28	E-UA-7014653-0-0	7014653-03	KEYBOARD ASSY.	-	-	1	1	-	-	-	-	-	-	-	-
29	29		5413097-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-	-	-
30	30		9009313-01	SUPPORT,C.BD.,FLAME RET.,NATURAL	4	4	4	4	-	-	-	-	-	-	-	-

REVISION HISTORY			BASIC PART NO: VT100		DRN: B. BLODGETT	DATE: 3-SEP-77	D I G I T A L			
ENG	ECO NUMBER	REV	SECTION B OF C				TITLE PARTS LIST			
JD	VT100-ML040	Z	SECTION. VARIATION INDEX		CHK'D: D. HEALY	DATE: 24-SEP-77	VT100 UNIT ASSY.			
GB	VT100-ML042	AA	[A] AA,AB,NA,NB,WA,WB,							
GB	VT100-ML043	AB	WC,WD,WE,WF,WG,WH							
GB	VT100-ML044	AC	[B] WJ,WK,WY,WZ,LA,LB,		DES.ENG.: E. WEDEKING	DATE: 26-JUN-78				
GB	VT100-ML045	AD	PA,PB,PC,PD,PE,PF							
GB	VT100-ML046	AE	[C] BA,BB,CA,CB,DA,DB				DOCUMENT NUMBER			
GB	VT100-ML047	AF			RESP.ENG.: G. DOUMANI	DATE: 26-JUN-78				
AJ	VT100-ML048	AH	[D]				SIZE	CODE	NUMBER	REV
GB	VT100-ML049	AJ								
			[E]		MFG.ENG.: K. HOFFMAN	DATE: 7-JUL-78	K	PL	VT100-0-DBP	AJ
			[F]		ASSEMBLY NUMBER:	TOP DOCUMENT NUMBER:	FILE NAME:		EDIT #	
					E-UA-VT100-0-0	#B-DD-VT100-0	MLOBAJ.PLS		19	
*THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.										
COPYRIGHT (C) 1982. DIGITAL EQUIPMENT CORPORATION *										

AUTOMATED BY PRTLST.3P(44)

PARTS LIST

SHEET B3 OF B3

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION											
					WJ	WK	WY	WZ	LA	LB	PA	PB	PC	PD	PE	PF

76 NOTE: ALTERNATE SHIPPING CONTAINERS FOR USE WITH VARIATIONS AS INDICATED
77 NOTE: (LABEL, SERIAL NUMBER) 3617674-08 MAYBE USED AS ALTERNATE PART NUMBER TO ITEM #50 (3617674-01)

D	I	G	I	T	A	L	TITLE	VT100 UNIT ASSY.	SECTION B	OF C	SIZE	CODE	DOCUMENT NUMBER	REV
											K	PL	VT100-0-DBP	AJ

ML3

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION					
					BA	BB	CA	CB	DA	DB
1	1	D-UA-7014653-0-0	7014653-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
2	2	E-IA-7014980-0-0	7014980-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
3	3	D-IA-7014976-0-0	7014976-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
4	4	D-IA-7014974-0-0	7014974-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
5	5		7014975-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
6	6		7014977-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
7	7	D-AD-7014979-0-0	7014979-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
8	8		7014978-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
9	9		5413009-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
10	10		7419836-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
11	11		3016080-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
12	12		9010007-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
13	13		9009967-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
14	14		3615680-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
15	15	A-PS-1700083-0-0	1700083-09	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
16	16	A-PS-1700083-0-0	1700083-10	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
17	17	D-UA-7014653-0-0	7014653-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
18	18		7414213-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
19	19		3613210-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
20	20		3613210-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
21	21		3613211-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
22	22		3700324-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
23	23	E-UA-VT1XX-AA-0	VT1XX-AA	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
24	24	A-PL-VT1XX-AB-0	VT1XX-AB	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
25	25		9006659-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
26	26		9007649-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
27	27		9010112-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
28	28	E-UA-7014653-0-0	7014653-03	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
29	29		5413097-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-
30	30		9009313-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-

REVISION HISTORY			BASIC PART NO: VT100		DRN: B. BLODGETT		DATE: 3-SEP-77		D I G I T A L	
ENG	ECO NUMBER	REV	SECTION C OF C							
JD	VT100-MLO40	Z	SECTION. VARIATION INDEX		CHK'D: D. HEALY		DATE: 24-SEP-77		TITLE PARTS LIST	
GB	VT100-MLO42	AA	[A] AA,AB,NA,NB,WA,WB,						VT100 UNIT ASSY.	
GB	VT100-MLO43	AB	WC,WD,WE,WF,WG,WH							
GB	VT100-MLO44	AC	[B] WJ,WK,WY,WZ,LA,LB,		DES.ENG.: E. WEDEKING		DATE: 26-JUN-78			
GB	VT100-MLO45	AD	PA,PB,PC,PD,PE,PF							
GB	VT100-MLO46	AE	[C] BA,BB,CA,CB,DA,DB						DOCUMENT NUMBER	
GB	VT100-MLO47	AF			RESP.ENG.: G. DOUMANI		DATE: 26-JUN-78			
AJ	VT100-MLO48	AH	[D]						SIZE CODE NUMBER REV	
GB	VT100-MLO49	AJ			MFG.ENG.: K. HOFFMAN		DATE: 7-JUL-78		K PL VT100-0-DBP	
			[E]							
			[F]		ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:		FILE NAME:	
					E-UA-VT100-0-0		E-DB-VT100-0		MLOBAJ.FLS	
									EDIT #	
									19	

*THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT (C) 1982. DIGITAL EQUIPMENT CORPORATION *

AUTOMATED BY PRTLST.3P(44)

P A R T S L I S T

SHEET C2 OF C3

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY	PER	VARIATION				
					BA	BB	CA	CB	DA	DB	
31	31		9010135-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
32	32	E-UA-7014653-0-0	7014653-05	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
33	33	E-UA-7014653-0-0	7014653-06	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
34	34	E-UA-7014653-0-0	7014653-07	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
35	35	E-UA-7014653-0-0	7014653-08	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
36	36	D-UA-5413097-0-0	5413097-03	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
37	37		5413009-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
38	38		3016080-53	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
39	39	D-IA-7014974-0-0	7014974-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
40	40	D-UA-7014653-0-0	7014653-10	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
41	41	D-UA-7014653-0-0	7014653-09	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
42	42		3616157-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
43	43	B-IA-7423018-0-0	7423018-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
44	44	B-MD-7423006-0-0	7423006-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
45	45		9008193-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
46	46		7016624-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
47	47	D-IA-7419469-0-0	7419469-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
48	48		1212405-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
49	49	A-PS-3617544-0-0	3617544-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
50	50	SEE NOTE	3617674-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
51	51		9010234-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
52	52	E-UA-5413097-0-0	5413097-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
53	53	E-IA-7017434-0-DBU	7017434-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
54	54		1217594-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
55	55		9009964-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
56	56		9009966-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
57	57		9009624-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
58	58		1218041-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
59	59		9009636-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
60	60	E-MD-7423954-0-DBU	7423954-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
61	61	D-UA-5413009-0-0	5413009-03	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
62	62	D-IA-7014978-0-0	7014978-03	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
63	63		3617880-03	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
64	64	B-IA-7017970-0-0	7017970-YA	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
65	65	D-UA-5413009-0-0	5413009-05	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
66	66		9000049-08	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
67	67	SEE NOTE	3700324-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
68	68	SEE NOTE	3700520-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
69	69	E-IA-7014980-0-0	7014980-04	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
70	70	D-AD-7018349-0-0	7018349-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
71	71	D-AD-7018349-0-0	7018349-05	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
72	72	E-UA-VT100-0-0	VT100-AA	VT100-A W 120V USA LINE CORD 170	4	-	8	-	16	-	
73	73	E-UA-VT100-0-0	VT100-AB	VT100-A W 240V USA LINE CORD 170	-	4	-	8	-	16	
74	74		3617905-01	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	
75	75		3617905-02	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	


D	I	G	I	T	A	L	TITLE	SECTION C OF C	SIZE	CODE	DOCUMENT NUMBER	REV
							VT100 UNIT ASSY.		K	PL	VT100-0-DBF	AJ

ML 3

LINE ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION					
				BA	BB	CA	CB	DA	DB

76 NOTE: ALTERNATE SHIPPING CONTAINERS FOR USE WITH VARIATIONS AS INDICATED
77 NOTE: (LABEL, SERIAL NUMBER) 3617674-08 MAYBE USED AS ALTERNATE PART NUMBER TO ITEM #50 (3617674-01)

D	I	G	I	T	A	L	TITLE	VT100 UNIT ASSY.	SECTION C OF C	SIZE	CODE	DOCUMENT NUMBER	REV
										K	PL	VT100-0-DBP	AJ



LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION				REFERENCE DESIGNATOR
					03	04	05	99	
1	1	D-MD-5013008-0-0	5013008-00	VT100 BASIC VIDEO	1	1	1	1	
2	2		1000005-00	6.8 MMF 100V 5%200PPM MICA	1	1	1	1	C9
3	3		1000014-00	68.0 MMF 100V 5%200PPM MICA	1	1	1	1	C11
4	4		1000016-00	100.0 MMF 100V 5%200PPM MICA	2	2	2	2	C21,C54
5	5		1000076-00	39 MFD 10V 10% S.TANT	1	1	1	1	C10
6	7		1017472-00	10 MFD 35V 450-10% AL EL	3	3	3	3	C1,C2,C3
7	8		1010274-01	.22 MFD 50V 480-20% 250 CER	13	13	13	13	C4-C6,C14,C15,C27-C29,C44,C45, CONT C55,C56,C59
8	9		1012784-00	.047 MFD 50V 480-20% CER	25	25	25	25	C7,C8,C13,C18,C19,C22,C24,C25, CONT C30-C43,C48-C50
9	10		1013466-12	2200.0 MMF 50V 10% X7R CER	1	1	1	1	C26
10	11		1100114-00	D 664 OS\75PCB PIV= 25V SP	11	11	11	11	D4-D8,D11-D16
11	12		1105796-00	1N 4004 PIV=400 I= 1A D041 SP	2	2	2	2	D9,D10
12	13		1109502-03	1N 4742A VZ= 12.0 5% 1W	1	1	1	1	D3
13	14		1110994-00	1N 751A VZ= 5.1 5% .40W	1	1	1	1	D1
14	15		1114974-00	1N 4741A VZ= 11.0 5% 1W	1	1	1	1	D2
15	16		1215006-06	SKT,IC 24PIN DIP 1IN GOLD	5	5	5	5	XE9,XE40,XE45,XE52,XE56
16	17		1211666-00	SKT,IC 18PIN DIP GOLD GOLD	1	1	1	1	J2
17	18		1214063-01	PCB,HEADER 50POS(2X20).150CC STR	1	1	1	1	J1
18	19		1214828-00	CONN, 25POS RCPT	1	1	1	1	J4
19	20		1214829-00	CARD EDGE 40PIN(2X20).125CC 90D	1	1	1	1	J3
20	21		1215048-01	PCB,HEADER 05PIN(1X07).098CC 90D	1	1	1	1	J5
21	22		1300005-07	R NETWORK 15-4.7K 5.0 % 16PIN	3	3	3	3	F8,F12,E59
22	23		1300219-00	68.0 .25 W 5.0 % CC	1	1	1	1	R40
23	24		1300229-00	100.0 .25 W 5.0 % CC	1	1	1	1	R34
24	25		1300250-00	150.0 .25 W 5.0 % CC	2	2	2	-	R51,R74
			CONT		-	-	-	3	R51,R68,R74
25	26		1300271-00	220.0 .25 W 5.0 % CC	1	1	1	1	R41
26	27		1300295-00	330.0 .25 W 5.0 % CC	3	3	3	3	R1,R46,R47
27	28		1300315-00	470.0 .50 W 5.0 % CC	1	1	1	1	R11

REVISION HISTORY			BASIC PART NO: 5413009			DRN: T. SHETRAWSKI			DATE: 30-MAR-78			D I G I T A L		
ENG	ECO NUMBER	REV	SECTION A OF A			CHK'D: T. SHETRAWSKI			DATE: 11-MAR-78			TITLE PARTS LIST		
RP	ML012	R	SECTION VARIATION INDEX			DES.ENG: D. PUCCI			DATE: 30-MAR-78			DOCUMENT NUMBER		
CJ	5413009-ML013	S	[A] 03,04,05,99			RESP.ENG.: D. PUCCI			DATE: 30-MAR-78			SIZE CODE NUMBER REV		
RP	5413009-ML014	T	[B]			MFG.ENG.: T. CORCIARI			DATE: 30-MAR-78			K PL 5413009-0-DBP AD		
RP	5413009-ML015	U	[C]			ASSEMBLY NUMBER:			TOP DOCUMENT NUMBER:			FILE NAME:		
RP	5413009-ML016	V	[D]			E-UA-5413009-0-0			B-DD-5413009-0-0			ML01AD.PLS		
DP	5413009-ML017	W	[E]											
DP	5413009-ML018	Y	[F]											
JD	5413009-ML019	Z	[H]											
RP	5413009-ML020	AA	[J]											
NW	5413009-ML021	AB	[K]											
RP	5413009-ML023	AC	[L]											
BE	5413009-ML025	AD	[M]											
			[N]											

THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT (C) 1982. DIGITAL EQUIPMENT CORPORATION

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY	PER VARIATION				REFERENCE DESIGNATOR
						03	04	05	99	
28	29		1300316-00	470.0	.25 W 5.0 %	CC	1	1	1	R21
29	30		1300365-00	1.0 K	.25 W 5.0 %	CC	2	2	2	R36,R67
30	31		1300398-00	1.80 K	.25 W 5.0 %	CC	1	1	1	R31
31	32		1300417-00	2.20 K	.25 W 5.0 %	CC	5	5	5	R18,R20,R22,R23,R27
32	33		1300426-00	2.70 K	.25 W 5.0 %	CC	1	1	1	R7
33	34		1300447-00	4.70 K	.25 W 5.0 %	CC	1	1	1	R25
34	35		1300479-00	10.0 K	.25 W 5.0 %	CC	4	4	4	R2,R6,R12,R26
35	36		1301317-00	10.0	.25 W 5.0 %	CC	1	1	1	R57
36	37		1301422-00	7.50 K	.25 W 5.0 %	CC	8	8	8	R59-R66
37	38		1301424-00	680.0	.25 W 5.0 %	CC	1	1	1	R37
38	39		1301425-00	300.0	.25 W 5.0 %	CC	1	1	1	R50
39	40		1301475-00	1.10 K	.25 W 5.0 %	CC	1	1	1	R32
40	42		1301874-00	5.60 K	.25 W 5.0 %	CC	1	1	1	R9
41	43		1301972-00	270.0	.25 W 5.0 %	CC	1	1	1	R38
42	44		1302379-00	75.0	.25 W 5.0 %	CC	5	5	5	R35,R45,R52,R54,R68
			CONT				-	-	-	R35,R45,R52,R54,
43	45		1302391-00	20.0 K	.25 W 5.0 %	CC	2	2	2	R43,R48
44	47		1303178-00	620.0	.25 W 5.0 %	CC	1	1	1	R49
45	48		1303187-00	820.0 K	.25 W 5.0 %	CC	1	1	1	R8
46	49		1304833-00	1.96 K	.25 W 1.0 %	RN55D-F10	1	1	1	R15
47	51		1313580-00	360.0	.25 W 5.0 %	CC	1	1	1	R39
48	52		1314673-00	36.0	.25 W 5.0 %	CC	1	1	1	R53
49	53		1501913-00	2N 2904A	PNP 600MW SI 60 40 Y		3	3	3	Q2,Q3,Q4
50	54		1503409-00	DEC6534D	PNP 310MW SI 40 50		1	1	1	Q1
51	55		1509524-00	2N 3904	NPN 310MW SI 40 40 M		1	1	1	Q5
52	56		1810694-06	XTAL 24.8832	MHZ		1	1	1	Y1
53	57		1814830-00	OSCILLATOR, XTAL	24.073 MHZ		1	1	1	E2
54	58		1909686-00	7404	INVERTER GATE-HEX 1I		1	1	1	E38
55	59		1909928-00	7416	INVERTER GATE-HEX 1I		2	2	2	E14,E18
56	60		1909929-00	7417	BUFFER GATE-HEX 1INP		1	1	1	E29
57	61		1910236-00	DEC 7426	NAND GATE-QUAD 2IN,0		1	1	1	E7
58	62		1910322-00	DEC 1488L	DRIVER,LINE,QUAD,EI		1	1	1	E39
59	63		1912847-00	LS157	MUX 1 OF 2(QUAD)		1	1	1	E1
60	64		1912697-00	LS174	FF-D HEX W/CLEAR		2	2	2	E49,E61
61	65		1912799-00	LS00	NAND-GATE-QUAD 2IN,P		2	2	2	E23,E34
62	66		1912803-00	LS04	INVERTER GATE,HEX		1	1	1	E19
63	67		1912815-00	LS30	NAND GATE-SINGLE 8IN		1	1	1	E3
64	68		1912818-00	LS38	NAND BUFFER-QUAD 2IN		1	1	1	E28
65	69		1912821-00	LS74	FF-D DUAL,EDGE TRIGG		2	2	2	E13,E22
66	70		1912842-00	LS138	DECODER-THREE INPUT,		1	1	1	E27
67	71		1912843-00	LS139	DECODER, 2 OF 4(DUAL		1	1	1	E31
68	72		1912851-00	LS193	COUNTER,SYNCHR,4BIT,		3	3	3	E21,E25,E30
69	73		1912863-00	LS273	FF-D OCTAL W/CLEAR		2	2	2	E16,E20
70	74		1913105-00	PB 8224C	DRIVER/GEN CLOCK F		1	1	1	E32
71	75		1913109-00	8228	BUFFER,DATA BASE FOR		1	1	1	E36
72	76		1913130-00	DEC 1489A	RECEIVER,LINE,QUAD,		2	2	2	E37,E44
73	77		1914084-00	74S299	SHIFT REG.,8BIT RIGH		1	1	1	E10
74	78		1914156-00	LM 393	VOLT.COMPARATOR DUAL		1	1	1	E48

D	I	G	I	T	A	L	TITLE	SECTION A OF A	SIZE	CODE	DOCUMENT NUMBER	REV
							VT100 BASIC VIDEO		K	PL	5413009-0-DBP	AD

LINE ITEM DOCUMENT NUMBER

PART NUMBER

DESCRIPTION

QTY PER VARIATION

03 04 05 99 REFERENCE DESIGNATOR


120 NOTE: FOR INDIVIDUAL FIELD SERVICE/CUSTOMER SPARES SHIPMENTS USE PACKAGING INSTRUCTION, A-SP-3700553-0-0;
121 NOTE: FOR BULK INTERPLANT SHIPMENTS USE PACKAGING INSTRUCTION, A-SP-3700428-0-0 VARIATION -02
122 NOTE: L2 REQUIRES THE INSERTION OF 1.5 TURNS OF 22 AWG BUSS WIRE SEE DETAIL ON E-UA-5413009-0-0.
123 NOTE: L3 AND L10 REQUIRES THE INSERTION OF 2.5 TURNS OF 22 AWG BUSS WIRE
124 NOTE: SEE DETAIL ON E-UA-5413009-0-0.

D	I	G	I	T	A	L	TITLE	VT100 BASIC VIDEO	SECTION A OF A	SIZE	CODE	DOCUMENT NUMBER	REV
										K	PL	5413009-0-DBP	AD


"THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF THE BELL TELEPHONE CORPORATION AND SHALL NOT BE COPIED OR REPRODUCED OR USED IN WHOLE OR IN PART AS TO ANYTHING THEREIN WITHOUT THE WRITTEN CONSENT OF THE BELL TELEPHONE CORPORATION."

CORPENT 67924 BELL TELEPHONE CORPORATION





ADVANCED VIDEO CONN.




GRAPHICS CONN



EDGE CONN




ORN. <i>100</i>	<i>2-1-78</i>	FIRST USED ON	VT100	000001
CHK'D <i>100</i>	<i>2-1-78</i>	TITLE	VT100	
ENG'D <i>100</i>	<i>2-1-78</i>	BASIC VIDEO		
PROD <i>100</i>	<i>2-1-78</i>			
NEXT HIGHER ASSY. (BVI1)				
E-UA-541 3009-O-O		SIZE	CODE	NUMBER
SCALE		D	CS	5413009-O-O-1
SHEET 1 OF 6		DIST.		



THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977 DIGITAL EQUIPMENT CORPORATION


DCS 5413009-0-1 AB



REVISIONS		
CHK	CHANGE NO.	REV.

TITLE VT100 BASIC VIDEO (RV3)
SCALE 1/2" = 1" SHEET 3 OF 6
SIZE CODE DCS 5413009-0-1 AB
NUMBER
REV.


THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1978 DIGITAL EQUIPMENT CORPORATION




REVISIONS		
CHK	CHANGE NO.	REV.

TITLE		SIZE CODE	NUMBER	REV.
VT100 BASIC VIDEO (BV4)		D CS	5413009-0-1	AB
SCALE		SHEET 4 OF 6	DIST.	

THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977 DIGITAL EQUIPMENT CORPORATION





THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977 DIGITAL EQUIPMENT CORPORATION

DUA 5412996-0-0 2

UJ999A JV

2415000 2015002E-P3
94V1 POWER SUPPLY
SIDE 3

REVISIONS		
CHK	CHANGE NO.	REV.

TITLE		SIZE CODE	NUMBER	REV.
H7831 POWER SUPPLY		DUA	5412996-0-0	R
SCALE 2/1		SHEET 2 OF 3		DIST.

TITLE		SIZE CODE		NUMBER		REV.	
H7831 POWER SUPPLY		D UA		5412996-0-0		1	
SCALE 2/1		SHEET 3 OF 3		DIST.			


LINE ITEM		DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION 00	REFERENCE DESIGNATOR
31	31		1114602-00	UES1302 PIV=100V I= 4A	2	D29,D33
32	32		1115112-00	PIV=800V I=1A	2	D19,D30
33	33		1115182-00	1N 5626 PIV=600 I= 3A	4	D16,D17,D18,D37
34	34		1115224-00	VOLT.TRANS.SUPPRESS 12.1	1	D35
35	35		1215228-00	HEAT SINKS,T0-220 01.25X0.87	1	
36	36		1212204-10	HEADER.156 3POS RT ANGLE	1	J2
37	38		1212297-05	MATE-N-LOK 06PIN(2X03).250CC HDR	1	J1
38	39		1211987-03	HEAT SINK,T0-3 1.750X01.7	1	
39	40		1213921-03	HEAT SINK,EXTRUSION 1.390X2.50	2	
40	41		1214789-00	INSERT,THREAD	4	
41	42		1210012-04	HEAT SINKS,	1	
42	43		1300219-00	68.0 .25 W 5.0 % CC	2	R9,R12
43	44		1300249-00	150.0 .50 W 5.0 % CC	1	R14
44	45		1300271-00	220.0 .25 W 5.0 % CC	1	R6
45	46		1300288-00	270.0 2.0 W10.0 % CC	1	R10
46	47		1300316-00	470.0 .25 W 5.0 % CC	2	R13,R46
47	48		1300365-00	1.0 K .25 W 5.0 % CC	3	R26,R35,R43
48	49		1300417-00	2.20 K .25 W 5.0 % CC	1	R8
49	50		1300426-00	2.70 K .25 W 5.0 % CC	1	R23
50	51		1300488-00	12.0 K .25 W 5.0 % CC	1	R4
51	52		1300496-00	15.0 K .25 W 5.0 % CC	1	R24
52	53		1300536-00	100.0 K 1.0 W10.0 % CC	2	R19,R20
53	54		1301317-00	10.0 .25 W 5.0 % CC	3	R7,R15,R25
54	55		1302091-00	330.0 K .25 W 5.0 % CC	2	R30,R51
55	56		1302177-00	47.0 K .25 W 5.0 % CC	1	R31
56	57		1302388-00	2.0 K .25 W 5.0 % CC	1	R29
57	58		1310867-00	680.0 K .25 W 5.0 % CC	1	R33
58	59		1303187-00	820.0 K .25 W 5.0 % CC	1	R5
59	60		1304833-00	1.96 K .25 W 1.0 % RN55D-F10	1	R3
60	61		1304854-00	5.11 K .25 W 1.0 % RN55D-F10	4	R32,R41,R48,R49
61	62		1304862-00	1.62 K .25 W 1.0 % RN55D-F10	1	R16
62	63		1304868-00	2.74 K .25 W 1.0 % RN55D-F10	1	R2
63	64		1305108-00	1.47 K .25 W 1.0 % RN55D-F10	1	R39
64	66		1309422-00	5.10 .50 W 5.0 % CF	1	R34
65	67		1309595-00	1.0 M .25 W 5.0 % CC	3	R36,R40,R42
66	68		1310188-00	300.0 10.0 W 5.0 % WW	1	R28
67	69		1311338-00	82.0 3.0 W 5.0 % WW	2	R21,R11
68	70		1305336-00	200.0 K .25 W 1.0 % RN55D-F10	1	R17
69	71		1313014-00	.01 3.75 W 3.0 % WW	3	R37,R44,R45
70	72		1317917-00	500.0 13.0 W 5.0 % WW	1	R27
71	73		1313341-00	*** THIS ITEM IS NOT USED ***	-	
72	74		1314270-00	5.0 15.0 % NTC THERM	2	R1,R50
73	75		1314350-00	1.0 2.0 W10.0 % FUSE	2	R22,R47
74	76		1510705-00	XA 05 NPN 500MW SI 60 50 P	2	Q3,Q6
75	77		1510706-00	XA 55 PNP 500MW SI 60 50 P	2	Q4,Q5
76	78		1517910-00	2N 6547 NPN T0-3	1	Q7
77	79		1514271-00	D 44Q1 NPN 31W SI	3	Q1,Q2,Q8
78	80		1614272-00	PULSE XFMR,4 WOUND	1	T3

D	I	G	I	T	A	L	TITLE	SECTION A OF A	SIZE	CODE	DOCUMENT NUMBER	REV
							H7831 POWER SUPPLY		K	PL	5412996-0-DBP	T


LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY	PER VARIATION	REFERENCE DESIGNATOR
					00		
79	81		1614273-00	PULSE XFMR, TRI-WOUND	1		T4
80	82		1615251-00	42.0 UH VARIABLE L 11A	1		L2
81	83		1615252-00	210.0 UH VARIABLE 2.75A	1		L1
82	84		1615253-00	XFMR P=AB S=25V	1		T2
83	85		1615668-01	XFMR P=240/480 S=120	1		T1
84	86		1910282-00	301AN OP AMP	1		E2
85	87		1911944-00	555CN TIMER, FUNCT. BLOCK	1		E4
86	88		1912048-06	DEC 7812 VOLT REG, FIX +12V	2		Z1, Z2
87	89		1914156-00	LM 393 VOLT. COMPARATOR DUAL	1		E1
88	90		1914250-00	3524 MODULATOR-REGULATING	1		E5
89	93		9006557-00	NUT, KEP 4-40X 1/4 AF	3		
90	97		9008172-00	WASHER, FLAT SST	4		
91	99		9006660-00	WASHER, FLAT SST	2		
92	100		9007793-01	SCREW, MACH PAN PHIL 6-	4		
93	101		9007801-00	WASHER, HELICAL SPLIT SST	4		
94	106		9009236-01	SCREW, TAP PAN PHIL THD CT 4-	4		
95	108		9009676-00	TERM, SOLDER BARRIER STR	1		
96	109		9009795-00	SCREW, SEMS PAN SLOT 10-	4		
97	110		9009798-00	SPACER, CLEAR HOLE RND CERAM .07	10		
98	112		1300197-00	33.0 .25 W 5.0 % CC	1		R52
99	113		1302466-00	100.0 K .25 W 5.0 % CC	1		R53
100	114		1305255-00	121.0 K .25 W 1.0 % RN55D-F10	1		R38
101	115		1001765-00	.005 MFD 100V 20% ZST DISC	1		C39
102	117		9006010-01	SCREW, MACH PAN PHIL 4-	3		
103	118		9009769-00	WASHER, RECTNGLR STEEL	1		
104	119		9006664-00	WASHER, FLAT SST	4		
105	120		9006563-00	NUT, KEP 8-32X 11/13AF	2		
106	121		1105796-01	5796-1PIV=400 I=1A D041	1		D26
107	122		1300285-00	270.0 .50 W 5.0 % CC	1		R55
108	123		1311867-00	.50 3.0 W 1.0 % WW	1		R56
109	124		9008264-00	MOUNT, CABLE TIE, ADHESIVE BACKE	1		
110	125		9007031-00	TIE, CABLE BUNDL. DIA 0- 3/4"=101	1		
111	126		9107278-09	TUBING, TEFLON .042ID	A/R		
112	127		1018980-00	6800.0 MMF 100V 1% MICA	1		C7
113	128		9107350-55	WIRE, 22AWG(07/30) IPVC 150V	A/R		
114	129		1312923-00	2.10 K .25 W 1.0 % RN55D-F10	1		R18
115	130		1210929-03	FUSE, SUB-MINI .750A, 125V, A	1		F1

116 NOTE: SEE E-UA-5412996-0-0 FOR ADDITIONAL INSERTION INFORMATION
117 NOTE: USE 1313191-00 UNTIL EXISTING STOCK HAS BEEN DEPLETED THEN USE 1317917-00.

D	I	G	I	T	A	L	TITLE		SECTION A	OF A	SIZE	CODE	DOCUMENT NUMBER	REV
							H7831 POWER SUPPLY				K	PL	5412996-0-DBP	T



ORIG. 1-1-68	3-1-77	FIRST CLASS ON		H7831		40-00-0	
CHRG. 1-1-68	3-1-77	TITLE		H7831			
EXTD. 1-1-68	3-1-77	POWER SUPPLY					
PROG. 1-1-68	3-1-77	NEXT HIGHER AGCY.					
PROD. 1-1-68	3-1-77	S-DO-5412996-C					
		SIZE	CODE	NUMBER		REV.	
		D	CS	5412996-C-1		U	
SCALE 1 +		DST.					
SHEET 1 OF 2							



THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1977, DIGITAL EQUIPMENT CORPORATION


NOTES:

1. CONNECT PLUG FROM ITEM 1 (7015053-00) TO J2 ON ITEM 2 (5412996).
2. INSTALL ITEM 3 AS SHOWN, TYP. 4 PLACES.
3. IDENTIFICATION: STAMP USING 1/8" CHARACTER HEIGHT AS INDICATED BELOW TO HIGHEST LEVEL OF SUBASSEMBLY SPECIFIED ON PURCHASE ORDER AND LOCATE APPROX. AS SHOWN ON DRAWING.
A.) PART NUMBER
B.) REVISION
C.) VENDOR IDENTIFICATION.
4. LOCATE ITEM NO. 4/5 APPROX. AS SHOWN.
5. ADD CSA LABEL 3613211-01 FOR ALL FAR EAST BUILT UNITS AS DIRECTED BY CORPORATE PRODUCT SAFETY. LABEL TO BE LOCATED UNDER SERIAL LABEL.
6. FOR INDIVIDUAL FIELD SERVICE OR CUSTOMER SPARES SHIPMENTS USE PACKAGING INSTRUCTIONS A-SP-3700552-0-0; FOR BULK INTERPLANT SHIPMENTS USE PACKAGING INSTRUCTION A-SP-3700437-0-0 VARIATION - 00

CAUTION: OFF SHEET PARTS LIST EXIST.
REFER TO K-PL-7014979-0-DBP


QUANTITY & VARIATION		DESCRIPTION		DWG. PART NO.		ITEM NO.	
THIRD ANGLE PROJECTION		UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES					
REMOVE BURRS AND BREAK SHARP CORNERS		ANGLES 10° 30°		GLASS OF ACCURACY		NOMINAL DIMENSION RANGE INCHES	
DO NOT SCALE DWG		SURFACE QUALITY IN		MICROINCHES		PREFERRED	
MATERIAL SEE PARTS LIST		FINISH		SCALE 1/1		SHEET 1 OF 1	
FINISH		NEXT HIGHER ASSY.		E-LA-VT100-0-0		SIZE CODE D AD	
		E-LA-VT100-0-0		SIZE CODE D AD		NUMBER 7014979-0-0	
		E-LA-VT100-0-0		SIZE CODE D AD		NUMBER 7014979-0-0	
		E-LA-VT100-0-0		SIZE CODE D AD		NUMBER 7014979-0-0	

REV.	CHG.	DATE	BY	APP.	DESCRIPTION
1		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
2		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
3		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
4		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
5		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
6		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
7		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
8		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
9		10/10/77	J. DEMARINIS		REVISED TO 10/10/77
10		10/10/77	J. DEMARINIS		REVISED TO 10/10/77



979

5413404
5013403C-PI L1



CS*ABCFHJKLM
SIDE 1

REVISIONS		
ONE	CHANGE NO.	REV.

TITLE		SIZE/CODE		NUMBER		REV
LK07 KEYBOARD		E	UA	5413404-0-0		D.
SCALE 2:1		SHEET 2 OF 3		DST		
2				1		

1979

L2



SIDE 2

LK07 KEYBOARD
5013403C-P1 5413404

REVISIONS		
CHK	CHANGE NO.	REV

TITLE		DATE		NUMBER		REV.	
LK07 KEYBOARD		EUA		5413404-0		D	
SCALE	2:1	SHEET	3	OF	3	DST	1

LINE	ITEM	DOCUMENT NUMBER
1	1	1
2	2	2
3	3	3
4	4	4
5	5	5
6	6	6
7	7	7
8	8	8
9	9	9
10	10	10
11	11	11
12	12	12
13	13	13
14	14	14
15	15	15
16	16	16
17	17	17
18	18	18
19	19	19
20	20	20
21	21	21
22	22	22
23	23	23
24	24	24
25	25	25
26	26	26
27	27	27
28	28	28
29	29	29
30	30	30
31	31	31
32	32	32
33	33	33
34	34	34
35	35	35
36	36	36
37	37	37
38	38	38
39	39	39
40	40	40
41	41	41
42	42	42
43	43	43
44	44	44
45	45	45
46	46	46
47	47	47
48	48	48
49	49	49
50	50	50
51	51	51
52	52	52
53	53	53
54	54	54
55	55	55
56	56	56
57	57	57
58	58	58
59	59	59
60	60	60
61	61	61
62	62	62
63	63	63
64	64	64
65	65	65
66	66	66
67	67	67
68	68	68
69	69	69
70	70	70
71	71	71
72	72	72
73	73	73
74	74	74
75	75	75
76	76	76
77	77	77
78	78	78
79	79	79
80	80	80
81	81	81
82	82	82
83	83	83
84	84	84
85	85	85
86	86	86
87	87	87
88	88	88
89	89	89
90	90	90
91	91	91
92	92	92
93	93	93
94	94	94
95	95	95
96	96	96
97	97	97
98	98	98
99	99	99
100	100	100

PART NUMBER

DESCRIPTION

QTY PER VARIATION
00

REFERENCE DESIGNATOR


1	D-MD-5013403-0-0	5013403-00	DRILL & ETCH DRAWING		C7
2		1000014-00	68.0 MMF 100V 5X200PPM MICA		C5
3		1000075-00	25 MFD 25V +75-10% AL EL		C6
4		1001634-00	1600.0 MMF 100V 5X200PPM MICA		C8
5		1005306-00	6.8MFD 35V 10% S.TANT		C1,C2,C4,C9-C11
6		1012784-00	.047 MFD 50V +80-20% CER		D8
7		1105275-00	D 672 TR= 15NS PIV= 60V SI		D1-D7
8		1110324-01	LED IMCD310MA PIV=3 .750 MIN. LE		J2
9		1215048-00	CONN SPOS RT ANGLE		R16,R42
10		1300309-00	390.0 .25 W 5.0 % CC		R15
11		1300315-00	470.0 .50 W 5.0 % CC		R10,R19,R21-R24
12		1300365-00	1.0 K .25 W 5.0 % CC		R26-R33,R38
13		1300439-00	3.30 K .25 W 5.0 % CC		R2,R3,R17,R25,R34-R37,R39-R41
14		1300479-00	10.0 K .25 W 5.0 % CC		R1
15		1301401-00	750.0 .25 W 5.0 % CC		R18,R20
16		1301425-00	300.0 .25 W 5.0 % CC		R5,R7,R9
17		1301874-00	5.60 K .25 W 5.0 % CC		R4,R6
18		1302391-00	20.0 K .25 W 5.0 % CC		R12
19		1303155-00	21.50 K .25 W 1.0 % RN55D-F10		R8
20		1303187-00	820.0 K .25 W 5.0 % CC		R11
21		1303312-00	10.0 K .25 W 1.0 % RN55D-F10		R14
22		1304833-00	1.96 K .25 W 1.0 % RN55D-F10		R13
23		1309412-00	18.20 K .25 W 1.0 % RN55D-F10		E9
24		1909686-00	7404 INVERTER GATE-HEX 1I		E1
25		1910406-00	75451 DRIVER PERIPH DUAL		E8
26		1910741-00	7406 INVERTER GATE-HEX 1I		Z1
27		1912536-01	7805 VOLT REG FIX +5V		E4
28		1912649-00	LS75 LATCH 4BIT,BISTABLE		E5
29		1912799-00	LS00 NAND-GATE-QUAD 2IN,P		E3
30		1912823-00	LS73 FF-JK DUAL W/CLEAR		

REVISION HISTORY			BASIC PART NO: 5413404		DRN: T SHETRAWSKI		DATE: 23-JUL-79		D I G I T A L	
ENG	ECO NUMBER	REV	SECTION A OF A		CHK'D: T SHETRAWSKI		DATE: 23-JUL-79		TITLE PARTS LIST	
RP	5413404-ML001	B	SECTION VARIATION INDEX		CHK'D: T SHETRAWSKI		DATE: 23-JUL-79		VT100 FULL KEYBOARD	
J.D	5413404-PN002	C	[A] 00							
J.B	5413404-PN003	D	[B]							
CJ	5413404-ML004	E	[C]		DES.ENG: M MORGESTERN		DATE: 23-JUL-79			
CJ	5413404-ML005	F	[D]							
			[E]		RESP.ENG.: M MORGESTERN		DATE: 23-JUL-79		DOCUMENT NUMBER	
			[F]							
			[H]						SIZE CODE NUMBER REV	
			[J]		MFG.ENG.: T CORCIARI		DATE: 23-JUL-79		K PL 5413404-0-DBP F	
			[K]							
			[L]		ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:		FILE NAME: EDIT #	
			[M]		D-UA-5413404-0-0				Z0783F.PLS 11	
			[N]							


"THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT (C) 1981. DIGITAL EQUIPMENT CORPORATION"

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION 00	REFERENCE DESIGNATOR
31	31		1912824-00	LS74 FF-D DUAL EDGE TRIGG	1	E6
32	32		1912844-00	LS151 MUX 1 OF 8 & DATA	1	E14
33	33		1913949-00	LS93 COUNTER, DECADE, 4BIT	2	E7, E10
34	34		1913950-00	LS156 DECODER, 2 OF 4(DUAL)	2	E11, E13
35	35		1914156-00	LM 393 VOLT. COMPARATOR DUAL	1	E2
36	36		2114137-51	UART MOS N-CHANNEL	1	E12
37	37		7013910-00	KEYBOARD ARRAY ASSY	1	
38	38		7014561-00	18 KEY NUMERIC PAD ASSY	1	
39	39		9006020-01	SCREW, PAN, PHIL 6-32X 1/4 SS	1	
40	40		9008185-00	NUT, KEP 6-32X1/4 AF	1	
41	41		9010033-00	SCREW, PAN, PHILLIPS 4-24 X 3/8	7	
42	42		1012312-01	.47 MFD 50V +80-20% CER	1	C3


D	I	G	I	T	A	L	TITLE	VT100 FULL KEYBOARD	SECTION A OF A	SIZE	CODE	DOCUMENT NUMBER	REV
										K	PL	5413404-0-DBP	F



THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977 DIGITAL EQUIPMENT CORPORATION




THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977, DIGITAL EQUIPMENT CORPORATION



REVISIONS		
CHK	CHANGE NO.	REV.

TITLE		SIZE CODE	NUMBER	REV.
VT100 FULL KEYBOARD (KB3)		DCS	5413404-0-1	F
SCALE	7 / 8	SHEET	3 OF 3	DIST.


1. THE NUMERIC KEY PAD IS NOT AVAILABLE ON THE E-UA-5413404-01 VARIATION.
2. STANDARD VT100 BASIC KEYCAP SET (12/4333-7Z, ITEM 5) AND NUMERIC PAD (12/4333-91, ITEM 6), SHOWN. FOR KEYCAP ARRANGEMENTS REFER TO DEC DRAWING NUMBER D-AR-7015765-0-1.
3. FOR INDIVIDUAL FIELD SERVICE/CUSTOMER SPARES SHIPMENTS, USE PACKAGING INSTRUCTIONS A-SP-3700555-0-0; FOR BULK INTERPLANT SHIPMENTS, USE PACKAGING INSTRUCTIONS A-SP-3700439-0-0 VARIATION -00.
4. INSTALL PLUNGER BELOW THIS KEY ON HOBI5 KEYCAP SET 12/4333-KZ. ALSO, FOR KEYCAP ARRANGEMENTS REFER TO DEC DRAWING D-AR-7015765-0-1.

[illegible]

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QUANTITY PER VARIATION									
					00	01	02	03	04	05	06	07	08	09
1	1	E-AD-5413404-0-0	5413404-00	VT100 FULL KEYBOARD	1	-	1	1	1	1	1	1	1	1
2	2	E-AD-5413404-0-0	5413404-01	KEYBOARD ASSY (64 KEYS)	-	1	-	-	-	-	-	-	-	-
3	3	C-AD-7015050-0-0	7015050-00	SPACE BAR ASSY	1	1	1	1	1	1	1	1	1	-
4	4		1214332-00	SW,ARRAY CAP ADAPTER	83	65	83	83	83	83	83	83	83	83
5	5		1214333-72	KEYCAP SET,VT100 64PCS	1	1	-	-	-	-	-	-	-	-
6	6		1214333-91	KEYCAP SET,LA120/34 VT100 18PCS	1	-	-	-	-	-	-	-	-	-
7	7		1214333-C0	KEYCAP SET,VT100-NA 82PCS	-	-	1	-	-	-	-	-	-	-
8	8		7420120-00	*** THIS ITEM IS NOT USED ***	-	-	-	-	-	-	-	-	-	-
9	9	D-AR-7015765-0-1		KEYBOARD/KEYCAP ASSY	REF	REF	REF	REF	REF	REF	REF	REF	REF	REF
10	10		1214333-J0	KEYCAP SET,VT100-WA 82PCS	-	-	-	1	-	-	-	-	-	-
11	11		1214333-W2	SW,KEY BD CAP COMP SET U3-W1	-	-	-	-	1	-	-	-	-	-
12	12		1214333-CP	KEYCAP SET,VT100-WB 82PCS	-	-	-	-	-	1	-	-	-	-
13	13		1214333-CB	KEYCAP SET,VT100-WB 82PCS	-	-	-	-	-	-	1	-	-	-
14	14		1214333-8U	KEYCAP SET,VT100-WB 82PCS	-	-	-	-	-	-	-	1	-	-
15	15		1214333-EY	KEYCAP SET,VT100-WB 82PCS	-	-	-	-	-	-	-	-	1	-
16	16		1214333-2Y	KEYCAP SET,VT100 64PCS	-	-	-	-	-	-	-	-	-	1
17	17		1214333-3W	KEYCAP SET,LA120/34 VT100 18PCS	-	-	-	-	-	-	-	-	-	1
18	18	D-AD-7015050-0-0	7015050-01	SPACE BAR ASSY. GRAY	-	-	-	-	-	-	-	-	-	1
19	19	A-SP-3700555-0-0	3700555-00	PKG KEYBOARD 7015765	1	1	1	1	1	1	1	1	1	1
20	20	A-SP-3700439-0-0	3700439-00	INSTR PKG. BULK CARTON 99-06476-	1	1	1	1	1	1	1	1	1	1
21	21	C-MD-7424160-0-0	7424160-00	SPACE BAR EQUALIZER CLIP	2	2	2	2	2	2	2	2	2	2

REVISION HISTORY			BASIC PART NO: 7015765		DRN: ANGEL COLON	DATE: 3 APR 78	DIGITAL				
ENG	ECO NUMBER	REV	SECTION A OF A					TITLE PARTS LIST			
---	INITIAL	F	SECTION. VARIATION INDEX		CHK'D: D. HEALY	DATE: 7 APR 78	KEYBOARD/KEYCAP ASSEMBLY				
JD	7015765-ML005	F	[A] 00,01,02,03,04,05,								
JD	7015765-ML006	H	06,07,08,09								
			[B]	DES.ENG.: E. WEDEKING		DATE: 10 MAY 78					
			[C]	RESP.ENG.: G. DOUMANI		DATE: 17 MAY 7	DOCUMENT NUMBER				
			[D]				SIZE	CODE	NUMBER	REV	
			[E]	MFG.ENG.: K. HOFFMAN		DATE: 10 MAY 78	K	PL	7015765-0-DBP	H	
			[F]	ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:	FILE NAME:		EDIT #		
				D-AD-7015765-0-0		#B-DD-7015765-0	Z1933H.PLS		6		
"THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT (C) 1981. DIGITAL EQUIPMENT CORPORATION "											

NOTES:
1. EXCEPT AS OTHERWISE NOTED, THE FOLLOWING TABLE (SHEET 2) LISTS VARIATION NUMBERS FOR 124335 (KEYCAPS) INDICATING THE SPECIFIC KEYBOARD POSITION OF EACH AS USED ON VARIOUS MODELS.



KEYBOARD CAP POSITIONS
(SEE NOTE 1 & TABLE, SHEET 2)

REVISIONS		REV.
DATE	CHANGE NO.	
5-2	7015765-M-002	A
<i>Rev. Submarine 47,000 28</i> L. KING		
<i>1-3-79</i> VT100 - PN026 B <i>Rev. R. P. Jones 12 Nov 79</i> E. C. JAMES		
VT100 MLO28 C <i>1-3-79 200 20</i> J. JAMES		
<i>Rev. P. Jones 1-16-80</i> VT100 MLO32 D J. JAMES		
PN026 E <i>Rev. P. Jones 3-30-80</i> 7015765-MLO03 F <i>Rev. 40-40-80 12-15-80</i> J. DEMARINIS		
<i>Rev. P. Jones 2-29-80</i> 7015765-MLO04 F <i>Rev. 40-40-80 12-15-80</i> F. HARDEN		
<i>Rev. 40-40-80 12-15-80</i> 7015765-MLO06 H <i>Rev. 40-40-80 12-15-80</i> G. BOURQUE		
<i>Rev. 40-40-80 12-15-80</i> 7015765-MLO07 J <i>Rev. 40-40-80 12-15-80</i> J. DEMARINIS		
<i>Rev. 40-40-80 12-15-80</i> 7015765-MLO08 K <i>Rev. 40-40-80 12-15-80</i> J. DEMARINIS		

DESCRIPTION						DWG./PART NO.	ITEM NO.
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES							
ANGLES $\pm .01^\circ$ SURFACE QUALITY IN		CLASS OF ACCURACY (CHECK ONE) MEDIUM ☐		NOMINAL DIMENSION RANGE INCHES OVER 12 TO 15 0-1E OVER 12 TO 15 0-1E OVER 12 TO 15 0-1E 15 TO 19 1A 15 TO 19 1A 15 TO 19 1A			
MICROMETERS		PREFERRED		0.004	0.008	0.012	0.016
				0.012	0.016	0.020	0.024
QUANTITY & VARIATION							
THIRD ANGLE PROJECTION		DRN. <i>Mander</i>		28 JUL 78	FIRST USED ON		
		CHK'D <i>J.D.</i>		POLYMER 78	VTI 00 4101030		
REMOVE BURRS AND BREAK SHARP CORNERS		ENG. <i>F.M.</i>		28 JUN 78	TITLE KEYBD CAP-POSITION ARRANGEMENT		
		PROJ. <i>E</i>		2-21-78			
		PROD. <i>E</i>		21 JUN 78			
DO NOT SCALE DWG		NEXT HIGHER ASSY.					
MATERIAL		D-AD-7015765-0-0		SIZE D	CODR AR	NUMBER 7015765-0-1	REV. J
FINISH		SHEET 1 OF 2		DIST.			

THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1978 DIGITAL EQUIPMENT CORPORATION

KEYCAP VARIATION (1214333-XX) POSITIONS (SEE NOTE 1, SHEET 1)

D	KEYBOARD CAP-POS- ITIONS (SEE SHEET 1)	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86																																																																																																																																																																																																																																																																																																																																																																																																																																																																																									
	VT100 (1214333-72) BASIC (1214333-91)	46	67	68	69	70	47	25	26	27	28	29	30	31	32	33	34	35	36	37	44	45	40	15	21	05	16	18	23	19	09	13	14	38	39	43	48	50	42	01	17	04	06	07	08	10	65	66	53	52	51	71	41	24	22	03	20	02	12	11	54	55	56	41	49	-	-	87	88	89	90	80	81	82	83	77	78	79	84	74	75	76	86	73	85																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	LA120 (1214333-64) BASIC (1214333-91)	46	59	62	60	61	47	25	26	27	28	29	30	31	32	33	34	35	36	37	44	45	40	15	21	05	16	18	23	19	09	13	14	38	39	43	48	50	42	01	17	04	06	07	08	10	57	58	53	52	51	63	41	24	22	03	20	02	12	11	54	55	56	41	49	-	-	87	88	89	90	80	81	82	83	77	78	79	84	74	75	76	86	73	85																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	LA34 (1214333-91) BASIC (1214333-95)	46	92	92	62	61	47	25	26	27	28	29	30	31	32	33	34	35	36	37	44	45	40	15	21	05	16	18	23	19	09	13	14	38	39	43	48	50	42	01	17	04	06	07	08	10	65	66	53	52	51	63	41	24	22	03	20	02	12	11	54	55	56	41	49	94	93	87	88	89	90	80	81	82	83	77	78	79	84	74	75	76	86	73	85																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	VT100 -NAE-NB DECFORM (1214333-C0)	46	96	97	98	99	47	25	26	27	28	29	30	31	32	33	34	35	36	37	44	45	40	15	21	05	16	18	23	19	09	13	14	38	39	43	48	50	42	01	17	04	06	07	08	10	65	66	53	52	51	71	41	24	22	03	20	02	12	11	54	55	56	41	A1	-	-	A2	A3	A4	A5	B7	B8	B9	A7	B4	B5	B6	A8	B1	B2	B3	B0	AG	A9																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	VT100-WACWB WORD PROC (1214333-J0)	46	E8	E9	F0	F1	47	25	26	27	28	29	30	31	32	33	34	E4	E5	E6	E7	45	40	D8	21	05	D9	E0	23	19	09	13	E1	E2	39	D6	E3	E0	42	D0	17	D1	D2	D3	08	10	65	D4	D5	D7	71	41	24	22	C1	C2	C3	C4	C5	C6	C8	C7	41	C9	-	-	F2	F3	F4	F5	F6	F7	F8	F9	H0	H1	H2	H3	H4	H5	H6	H9	H7	H8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																												
	VT132-AAEAB COMP SET (1214333-W2)	46	67	68	69	70	47	25	26	27	28	29	30	31	32	33	34	35	36	37	44	45	40	15	U	05	16	18	23	19	09	13	14	38	39	43	U3	50	42	01	17	04	06	07	08	10	65	66	53	52	51	71	41	24	22	03	20	02	12	11	54	55	56	41	49	-	-	U4	U5	U6	W1	80	81	82	WK	77	78	79	U8	74	75	76	U0	73	U9																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	VT100-WC1WD 1214333-CPFR CANADIAN	46	E8	E9	F0	F1	47	25	CC	CD	28	29	CE	31	32	33	34	E4	E5	CF	E7	45	40	D8	21	05	D9	E0	23	19	09	13	E1	CH	CL	D6	E3	50	42	D0	17	D1	D2	D3	08	10	65	D4	53	CM	D7	71	41	24	22	C1	C2	C3	C4	C5	C6	C8	CW	41	CK	-	-	F2	F3	F4	F5	F6	F7	F8	F9	HO	H1	H2	H3	H4	H5	H6	H9	WJ	H8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																											
	VT100-WF4WF 1214333-CB FRENCH	AP	E8	E9	F0	F1	47	25	CC	MI	28	29	KI	J7	J8	J9	J5	DA	DB	8E	DD	45	40	EU	21	05	DF	DM	18	03	13	DJ	BY	L7	DK	EW	50	BN	EB	17	DL	DM	DN	08	10	65	D4	K6	DP	DR	71	W0	L5	22	C1	DE	DS	DT	DV	DWDY	D2	WO	EC	-	-	F2	EA	ED	EE	EF	F7	AK	EH	EJ	EK	EL	ET	EM	EP	ER	ES	H8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																														
	VT100-WG4WH 1214333-BU DUTCH	46	E8	E9	F0	F1	47	72	BA	B7	28	29	88	31	J8	J9	8D	8F	8H	8E	E7	45	40	D8	21	05	D9	E0	23	19	09	13	E1	8K	8C	DC	E3	50	42	D0	17	D1	D2	D3	08	10	65	D4	8L	8M	D7	71	41	24	22	C1	C2	C3	C4	C5	C6	C8	BP	BR	41	BS	-	-	F2	F3	F4	F5	F6	F7	F8	F9	HO	H1	H2	H3	H4	H5	H6	H9	H7	H8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																										
VT100-WY4WK 1214333-EY GERMAN	BH	E8	E9	F0	F1	47	25	CC	MI	28	29	KI	J7	J8	J9	J5	DA	DB	8E	DD	45	40	EU	21	05	DF	DM	18	03	13	DJ	BY	L7	DK	EW	50	BN	EB	17	DL	DM	DN	08	10	65	D4	K6	DP	DR	71	W0	L5	22	C1	DE	DS	DT	DV	DWDY	D2	WO	EC	-	-	F2	EA	ED	EE	EF	F7	AK	EH	EJ	EK	EL	ET	EM	EP	ER	ES	H8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																															
VT100 SPECIAL DARK GRAY 1214333-2Y	JP	2R	2S	2T	2U	1R	ON	OP	OR	OS	OT	OU	OW	OY	OZ	1A	1B	1C	1D	1M	1N	1H	OB	OJ	Z1	OC	OE	OL	OF	Z5	Z9	OA	1E	1F	1L	1S	1U	1K	Y7	OD	ZO	Z2	Z3	Z4	Z6	2W	2P	1Z	1Y	1W	2W	1J	OM	OK	Y9	OH	Y8	Z8	Z7	2A	2B	2C	1J	1T	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-

1217800-B8


1217800-B9

1217800-C1

1217800-B5-

REVISIONS		
CHK	CHANGE NO.	REV.

TITLE		KEYBD CAP-POSITION ARRANGEMENT		SIZE		CODE		NUMBER		REV	
				D		AR		7015765 - 0 - 1		J	
SCALE		NONE		SHEET		2		OF		2	
				DIST.							



THIS DRAWING AND SPECIFICATIONS, WHETHER AND THE PROPERTY OF BALL BROTHERS, INC., AND SHALL NOT BE REPRODUCED OR USED IN ANY MANNER WITHOUT THE WRITTEN PERMISSION OF BALL BROTHERS, INC. EXCEPT AS MAY BE OTHERWISE SPECIFIED.


NOTES:
1) FEEDBACK TRANSFORMER REPLACEMENT 3014590-01
2) PRINTED CIRCUIT BOARD REPLACEMENT 3014590-02

CHK	CHANGE NO	REV

COPIED BY WRITTEN PERMISSION
OF BALL BROTHERS INC.

SIGNATURES		DATE
DRN.	<i>[Signature]</i>	9-8-78
CHK'D.	<i>[Signature]</i>	12-6-78
ENG.	<i>[Signature]</i>	12-6-78
PROJ. ENG.	<i>[Signature]</i>	12-6-78
PROD.		
SCALE		
ETCH REV.		
P.C. DESIGN DATA BASE REV.		
NEXT HIGHER ASSY.		

TITLE		REV
digital		
SCHEMATIC		
TVX120/DEC 12 VOLT		
SIZE	CODE	NUMBER
1	D	CS 3014590-0-1
MS#180297		




REF SYM	DESCRIPTION	PART NUMBER
RESISTOR, FIXED, CARBON, 5%, 1/4W UNLESS NOTED		
R101	47	70-16-0470
R102	30	70-16-0300
R103	47	70-16-0470
R104	220, 1/2W	1-011-2254
R105	820, 1/2W	1-011-2258
R106	470	70-16-0471
R107	360	70-16-0361
R108	100K	70-16-0104
R109	180, 1/2W	1-011-2252
R110	VAR; 250 20K, CO VERT HGT	70-89-0251
R111	12, 1/2W	1-011-2224
R112	15, 1/2W	1-011-2228
R113	NOT USED	
R114	1.5K, 1/2W	1-011-2274
R115	NOT USED	
R116	82K	70-16-0823
R117	100K, 20P	1-011-5435
R118	30K, 1/2W	1-011-2305
R119	9.1K	70-16-0912
R120	8.2M	70-16-0825
R121	100K	70-16-0104
R122	VAR; 2.5M 20K, CO FOC ADJ	1-011-5568
R123	NOT USED	
R124	510	70-16-0511
R125	7K	70-16-0102
R126	20K	70-16-0203
R127	3.3K	70-16-0332
R128	15K	70-16-0153
R129	2.4K	70-16-0242
R130	56 10; 3W, WW	1-011-2521
R131	1.2; 1/2W, CO	1-011-2520
R132	1.2 10K; 2W, WW	1-011-1395
R133	8.8K	70-16-0682
R134	1.8, 2W	1-011-2417
R135	NOT USED	
TRANSFORMER		
T2	HIGH VOLTAGE	6-003-0586
T101	HORIZ DRIVER	1-017-5402
MISCELLANEOUS		
	*CRT SOCKET	1-022-0427
	WIRE STRD GRN	1-038-0345
	HEATSINK	1-015-5059
	WIRE STRD BLU	1-038-0346
	WIRE STRD RED	1-038-0342
	CONTACT, FEMALE 6 2	1-034-6362
	MONSQR 6-32X1/4	3-011-0310
	NUT 6-32	3-012-0181
	UK NSHR #6	3-013-0180
	PWB	1-029-0442
	CONTACT, MALE	1-034-0295
	CONN SHELL, 1 CONT FEMALE	1-034-0323
WIRE TERMINATION DATA		
E103	CRT SOCKET YEL LEAD	
E105	CRT SOCKET BRN LEAD	
E107	CRT SOCKET BLK LEAD	
E108	CRT SOCKET RED LEAD	
E109	CRT SOCKET WHT LEAD	
E110	GRN WIRE 6.5 INCHES	
E111	CRT SOCKET GRN LEAD	
E112	BLU WIRE, 10 INCHES	
E113	RED WIRE, 10 INCHES	

NOTES:
1. REFERENCE SCHEMATIC 1-024-0603
2. ALL REFERENCE SYMBOL NUMBERS 1 TO 99 ARE USED FOR ALL OFF BOARD COMPONENTS AND NUMBERS 100 TO 999 ARE USED FOR THE PWA COMPONENTS.
3. ALL PWA COMPONENTS PRECEDED WITH AN ASTERISK ARE NOT PART OF THE BASIC BOARD 6-200-0001.

PARTS LIST, TVX 120/DEC		
REF SYM	DESCRIPTION	PART NUMBER
A101	RES TRIM, 80K, VERT HOLD	1-011-8008
A102	RES TRIM, 20K, VERT LIM	1-011-8005
A103	RES TRIM, 2.5K, VIDEO CENTER	1-011-8001
CAPACITOR, FIXED, UF UNLESS NOTED		
C101	270PF 5%, 500V, DM	1-012-0396
C102	.005 20K, 100V, CO	10-12-7508
C103	.22 10K, 100V, MY	1-012-2277
C104	.22 10K, 100V, MY	1-012-2277
C105	.68, 50V, E	1-012-2284
C106	470, 6.3V, E	1-012-2158
C107	NOT USED	
C108	22, 25V, E	1-012-1340
C109	.01 20K, 1000V, CO	1-012-2214
C110	.02 20K, 1000V, CO	1-012-2217
C111	.01 20K, 1000V, CO	1-012-2214
C112	.0022 10K, 630V, MY	1-012-2254
C113	.0047 20K, 630V, MY	1-012-2278
C114	.01 20K, 100V, CO	10-12-7209
C115	1, 50V, E	1-012-2189
C116	50, 50V, E	1-012-2157
C117	.047 20K, 250V, MY	1-012-2240
C118	220, 25V, E	1-012-2255
C119	10 10K, 100V, MY	1-012-2255
C120	.02 20K, 500V, CO	1-012-0780
C121	50, 50V, E	1-012-2157
C122	.022 10K, 250V, PP	1-012-2297
C123	10, 25V, ER	1-012-2273
C124	10, 28V, ER	1-012-2273
DIODE		
D101	00424	1-021-0424
D102	00410	1-021-0410
D103	00410	1-021-0410
D104	00410	1-021-0410
D105	00410	1-021-0410
D106	00410	1-021-0410
D107	00410	1-021-0410
D108	NOT USED	
D109	00410	1-021-0410
D110	00403	1-021-0403
D111	00458	1-021-0458
D112	00458	1-021-0458
D113	00403	1-021-0403
D114	00410	1-021-0410
FUSE		
F101	2A-125V P100	1-028-0247
CONNECTORS		
J102	CONNECTOR, 4 PIN MALE	1-039-0146
J102	NOT USED	
J104	CONNECTOR, 7 PIN MALE	1-039-0145
COIL		
L1	VERTICAL CHOK	6-003-0572
L2	DEFLECTION, TVX 120/12V	1-023-0248
L101	560HM	1-016-0302
L102	LINEARITY	1-016-0328
L103	WIDTH	1-016-0303
TRANSISTOR		
Q101	2N5830	1-015-1172
Q102	2N5027	1-015-1157
Q103	MPS-465	1-015-1186
Q104	MJE3055	1-015-1156
Q105	2N4134	1-015-1139
Q106	2N4124	1-015-1139
Q107	MPS-405	1-015-1159
Q108	6N407	1-015-1210


THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF BALL BROTHERS, INC. AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT ©



- GENERAL NOTES: UNLESS OTHERWISE SPECIFIED
1. ALL RESISTORS 1/4W, 5%, VALUE IN OHMS.
 2. ALL CAPACITOR VALUES IN MICROFARADS. FOR CAPACITOR TYPES, SEE NOTE NO. 9.
 3. DENOTES J101 PC CARD EDGE CONNECTOR.
 4. DENOTES CONNECTION TO OFF BOARD COMPONENTS.
 5. REFERENCE DESIGNATIONS NOT USED: J103, C107, C108, R101, R113, R115, R123
 6. LAST REFERENCE DESIGNATION USED: R134, C124
 7. PROTECTIVE ARC GAPS ARE AN INTEGRAL PART OF PRINTED WIRE BOARD.
 8. THE PWB CIRCUIT GROUNDS ARE BROUGHT OUT SEPARATELY TO PINS 1, 5 AND 10 OF J101. PWB CIRCUIT GROUNDS FOR PINS 1 AND 5 OF J101 ARE CONNECTED TOGETHER BY A JUMPER WIRE ON THE BOARD AND ARE CONNECTED TO CHASSIS GROUND VIA A WIRE FROM E110.
 9. DENOTES HEATSINK
 10. = DIPPED MICA
 11. = CERAMIC DISC
 12. = MYLAR
 13. = ELECTROLYTIC AXIAL
 14. = ELECTROLYTIC RADIAL
 15. = POLYPROPYLENE
 16. GROUNDED TO AQUADAG (BY SPRING)

COPIED BY WRITTEN PERMISSION OF BALL BROS.

DRN. Jim D. Angel	7/20/78	FIRST USED ON	VT100
CHK'D. R. B. Brown	12-6-78	TITLE	SCHEMATIC
ENG. R. B. Brown	12-6-78		TVX120/DEC
PROD. ENG. R. B. Brown	12-6-78		12 VOLT
PROD.			
NEXT HIGHER ASSY.			
E-UA-VT100-0-0	SIZE	CODE	NUMBER
SCALE NONE	D	CS	3014590-0-1
SHEET 2 OF 2	DIST.		




- NOTES:
1. INSERT CONN. (ITEM 3) INTO CONN. OF (ITEM 2) FOR TESTING OPTION.
 2. PACKAGING: WHEN SHIPPED, MATERIAL SHALL BE ADEQUATELY PROTECTED FROM HANDLING AND SHIPPING DAMAGE USING DIGITAL PACKAGING INSTRUCTION A-SP-3700538-00.
 3. LOCATE APPROX. AS SHOWN ON DWG.
 4. TORQUE (ITEM 6) TO 6.0 IN-LBS $\pm$.5 IN-LBS.
 5. TORQUE (ITEM 7) TO 8.0 IN-LBS $\pm$.5 IN-LBS.

CAUTION: OFF SHEET PARTS LIST EXISTS.
REFER TO 4-FL-VTXX-AA-08P

QUANTITY & PART NUMBER		DESCRIPTION		PART NUMBER		DATE	
1	VTXX-AA-01	20MA CURRENT LOOP OPTION	VTXX-AA-01	20-00-00	20-00-00	20-00-00	20-00-00
2	VTXX-AA-02	20MA CURRENT LOOP OPTION	VTXX-AA-02	20-00-00	20-00-00	20-00-00	20-00-00
3	VTXX-AA-03	20MA CURRENT LOOP OPTION	VTXX-AA-03	20-00-00	20-00-00	20-00-00	20-00-00
4	VTXX-AA-04	20MA CURRENT LOOP OPTION	VTXX-AA-04	20-00-00	20-00-00	20-00-00	20-00-00
5	VTXX-AA-05	20MA CURRENT LOOP OPTION	VTXX-AA-05	20-00-00	20-00-00	20-00-00	20-00-00
6	VTXX-AA-06	20MA CURRENT LOOP OPTION	VTXX-AA-06	20-00-00	20-00-00	20-00-00	20-00-00
7	VTXX-AA-07	20MA CURRENT LOOP OPTION	VTXX-AA-07	20-00-00	20-00-00	20-00-00	20-00-00
8	VTXX-AA-08	20MA CURRENT LOOP OPTION	VTXX-AA-08	20-00-00	20-00-00	20-00-00	20-00-00

THIS DRAWING AND SPECIFICATIONS, HEREIN, AND THE
PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL
NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN
PART OR THE BASIS FOR THE PRODUCTION OR SALE OF
ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1980 DIGITAL EQUIPMENT CORPORATION

COMPONENT SIDE VIEW



NOTES:

STEP 6
REPEAT

Y AXIS
X AXIS

CHANGE NO	REV
5413206-0000	C
REVISED & REDRAWN	
J. DEMARINIS	10-16-80

ETCH REV. D

SIGNATURES	DATE	
DRN. V. PARECHANIAN	11-77	digital
CHK. D. M. MORTENSEN	11-77	
MECH. ENG. M. MORTENSEN	4-78	
PROJ. ENG. N. FORRESTER	5-78	
PROD. R. PUCCI	6-78	
SCALE 2	1	
SHT. 1	OF 1	
NEXT HIGHER ASSY. B-DD-5413206-0		
TITLE	20 MA ADAPTER	
SIZE CODE	D	
NUMBER	5413206-3-0	
REV	C	



WO#150220

SHEET A1 OF A1

REVISION HISTORY			BASIC PART NO: 5413206			D I G I T A L		
ENG	ECD NUMBER	REV	SECTION A OF A	DRN:	T. SHETRAWSKI	DATE:	30-MAR-78	
---	INIT	B	SECTION VARIATION INDEX	CHK'D:	T. SHETRAWSKI	DATE:	30-MAR-78	TITLE
JB	5413206-PN001	C	(A) 00					PARTS LIST
			(B)					20 MA ADAPTER
			(C)	DES.ENG:	M. MORGENSTERN	DATE:	30-MAR-78	
			(D)					
			(E)					DOCUMENT NUMBER
			(F)	RESP.ENG.:	M. MORGENSTERN	DATE:	30-MAR-78	
			(H)					SIZE CODE NUMBER
			(J)					REV
			(K)	MFG.ENG.:	T. CORCIARI	DATE:	30-MAR-78	K PL 5413206-0-DBP C
			(L)					
			(M)	ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:		FILE NAME:
			(N)	D-UA-5413206-0-0		VI100		13206C.PLS
								EDIT #
								6

"THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT (C) 1980, DIGITAL EQUIPMENT CORPORATION "

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1977 DIGITAL EQUIPMENT CORPORATION



NOTE :
I. * OPTIONAL


DRN	30 MAR 77	FIRST USED ON	VT100	digital
CHK'd	6/2/78	TITLE	20 MA	
ENG	1/13/78		ADAPTOR	
PROJ. ENG.	5/1/78			
PROD. Richard Price	5/13/78			
NEXT HIGHER ASSY.				
D-UA-5413206-0-0		SIZE	NUMBER	REV
SCALE		D	CS 5413206-0-1	C
SHEET	OF	DIST.		

THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1977, DIGITAL EQUIPMENT CORPORATION


WIRE TABLE							
ITEM NO.	AWG	COLOR	FROM	WITH	TO	WITH	REMARKS
10	22	YELLOW	PIN 8		ITEM 1 GND		
		GREEN	7		R+		
		WHITE	5		T+		
		RED	3		R-		
		BLACK	2		T-		
10	22	VIOLET	PIN 1		ITEM 1 -		

NOTES:

1. FOR INDIVIDUAL FIELD SERVICE / CUSTOMER SPARES SHIPMENTS USE PACKAGING INSTRUCTIONS A-SP-3700550-0-0. FOR BULK INTERPLANT SHIPMENTS USE PACKAGING INSTRUCTIONS A-SP-3700429-0-0, VARIATION - 03



VIEW A-A
(REAR VIEW)




CAUTION: OFF SHEET PARTS LIST EXISTS,
SEE K-PL-7015273-0-DBP.

DESCRIPTION		DWG./PART NO.	ITEM NO.
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES			
ANGLES 10° 30°	CLASS OF ACCURACY (CHECK ONE)	NOMINAL DIMENSION RANGE IN INCHES	
SURFACE QUALITY IN	MEDIUM	OVER 0 TO 0.2	OVER 0.2 TO 0.5
QUANTITY & VARIATION	PREFERRED	OVER 0.5 TO 1.0	OVER 1.0 TO 2.0
THIRD ANGLE PROJECTION	REMOVE BURRS AND BREAK SHARP CORNERS	OVER 2.0 TO 4.0	OVER 4.0 TO 12.0
DO NOT SCALE DWG	NEXT HIGHER ASSY.	OVER 12.0 TO 40.0	OVER 40.0 TO 100.0
MATERIAL SEE PARTS LIST	E-UA-VTIXX-AA-0	SCALE 2/1	SHEET 1 OF 1
FINISH			

DRN. 5/8/77	5/8/77	FIRST USED ON	VT100
CHK'D. 5/8/77	5/8/77	TITLE	20 MA ADAPTER ASSY
ENG. 5/8/77	5/8/77	SIZE CODE	D
PROD. 5/8/77	5/8/77	NUMBER	7015273-0-0
		REV.	B

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1978, DIGITAL EQUIPMENT CORPORATION"

WIRE TABLE						
ITEM NUMBER	DESCRIPTION		FROM		TO	
	AWG	COLOR	CONNECTION	WITH	CONNECTION	WITH
1	24	BLK	J1-1	3	J2-1	3
			J1-2		J2-2	
			J1-3		J2-3	
			J1-4		J2-4	
			J1-6		J2-6	
	24	BLK	J1-7	3	J2-7	3



LEGEND		
NUMBER	DIM 'X' VARIATION	DIM 'Y' (PRE CUT) REF
7015506-08	2.0 IN $\pm$.25 IN.	2.75 IN.

12	CONTACT, PIN	1214979-00	3
2	HOUSING, 7 CONN	1215047-01	2
A/R	WIRE, 24AWG, STRD (BLK)	9107450-00	1

DESCRIPTION			DWG./PART NO.		ITEM NO.		
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES							
ANGLES ±0° 30'	CLASS OF ACCURACY	NOMINAL DIMENSION RANGE INCHES					
		OVER 0 TO 0.2	OVER 0.2 TO 1.2	OVER 1.2 TO 4.0	OVER 4.0 TO 12.0	OVER 12.0 TO 40.0	OVER 40.0 TO 80.0
SURFACE QUALITY IN	(CHECK ONE)						
	MEDIUM ☐	±.004	±.008	±.012	±.018	±.024	±.04
MICROINCHES	PREFERRED ☐	±.012	±.016	±.025	±.04	±.062	±.1

THIRD ANGLE PROJECTION	DRN. <i>6/2/78</i> 50-78	FIRST USED ON	VT100	digital
REMOVE BURRS AND BREAK SHARP CORNERS	CHK'D <i>6/2/78</i> 50-78	TITLE	CABLE, INTERNAL 20 MA ADAPTOR	
DO NOT SCALE DWG	PROJ. ENG. <i>6/2/78</i> 50-78	SIZE	CODE	NUMBER
MATERIAL SEE PARTS LIST	PROD. <i>6/2/78</i> 50-78	E- UA-VTXX-AA	C	IA 7015506-0-0
FINISH	NEXT HIGHER ASSY.	SCALE NONE	DIST.	REV. A
		SHEET 1 OF 1		

REVISIONS		REV.
CHK	CHANGE NO.	A
7015506-ML001	9-20-78	
C. JAMES	Richard A. Purca	11-1-79

WORKPAGE P-1558

DEC FORM NO.

This drawing and specifications, herein, are the property of Digital Equipment Corporation and shall not be reproduced or copied or used in whole or in part as the basis for the manufacture or sale of items without written permission.

LEGEND

NUMBER	DIM "X" VARIATION	DIM "Y" (PRECUT) REF
BC05F-15	15 FT. $\pm$ 3 IN.	15 FT. .75 IN. $\pm$ 3 IN.
BC05F-9	9 FT. $\pm$ 2 IN.	9 FT. .75 IN. $\pm$ 2 IN.
BC05F-04	4 FT. $\pm$ 1 IN.	4 FT. .75 IN. $\pm$ 1 IN.
BC05F-25	25 FT. $\pm$ 3 IN.	25 FT. .75 IN. $\pm$ 3 IN.
BC05F-30	30 FT. $\pm$ 2%	30 FT. .75 IN. $\pm$ 2%
BC05F-45	45 FT. $\pm$ 2%	45 FT. .75 IN. $\pm$ 2%
BC05F-50	50 FT. $\pm$ 2%	50 FT. .75 IN. $\pm$ 2%
BC05F-90	90 FT. $\pm$ 2%	90 FT. .75 IN. $\pm$ 2%
BC05F-B0	200 FT. $\pm$ 2%	200 FT. .75 IN. $\pm$ 2%
BC05F-C0	300 FT. $\pm$ 2%	300 FT. .75 IN. $\pm$ 2%
BC05F-E0	500 FT. $\pm$ 2%	500 FT. .75 IN. $\pm$ 2%

WIRE TABLE


ITEM NO	DESCRIPTION	FROM	TO
3	22 BLK	P1-2	P2-3
3	22 RED	P1-3	P2-2
3	22 WHT	P1-5	P2-7
3	22 GRN	P1-7	P2-5

LEGEND CONT.

NUMBER	DIM "X"	DIM "Y" REF
BC05F-E5	550 FT. $\pm$ 2%	550 FT. .75 IN. $\pm$ 2%
BC05F-L0	1000 FT. $\pm$ 2%	1000 FT. .75 IN. $\pm$ 2%

NOTES:

1. ASSEMBLE CABLE I.D. LABEL TO AREA AS SHOWN BELOW.



CAUTION: FOR OFF SHEET PARTS LIST
SEE K-PL-BC05F-0-0.

REV.	CHANGE NO.	DATE	BY	CHK'D	DATE	BY	CHK'D
A	BC05F-00001	11-8-71	R. FITCH				
B	LA36-00119	11-9-71	Robert Fitch				
C	BC05F-00002	7/18/75	J. BITTO				
D	BC05F-ML003	22 JUN 76	R. FITCH				
E	BC05F-MK004	27 May 81	J. DESUK				
F	BC05F-MK004	17 Dec 81	R. HARRINGTON				

FIRST USED ON OPTION MODEL DF11	QTY.	DESCRIPTION	PART NO.	ITEM NO.
PARTS LIST				
UNLESS OTHERWISE SPECIFIED DIMENSION IN INCHES TOLERANCES DECIMALS $\pm$.005 FRACTIONS $\pm$ 1/64 ANGLES $\pm$ 0°30' FINAL SURFACE QUALITY REMOVE BURRS AND BREAK SHARP CORNERS	DRN R. Fitch 10/8/71	DATE 10/8/71	digital EQUIPMENT CORPORATION JAYNARD, MASSACHUSETTS	
MATERIAL FINISH	PROJ. ENG. Robert Fitch 10/19/71	DATE 10/19/71	TITLE CABLE INTERFACE BC05F	
NEXT HIGHER ASSY H		DATE 11-26-71	REV. E	
SCALE SHEET 1 OF 1		SIZE CODE CUABC05F 0-0		

DEC FORM NO.
DRC

4

3

2

1


mk

SIZE CODE
CUABC05F 0-0

B


THIS DRAWING AND SPECIFICATIONS, HEREIN, AND THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1974 DIGITAL EQUIPMENT CORPORATION

COMPONENT SIDE VIEW



5.187 REF.
131.75 MM.

5.60 REF.
142.24 MM.



NOTES: J1 CONN MOUNTED ON SIDE 2

STEP E → Y AXIS — STEP — TIMES 2 ML 2
REPEAT → X AXIS 2.50 STEP 1 TIMES

CHANGE NO. REV	
5413097-0-0 F	
REDRAWN BY	
H. PUCCI	
DATE	10/24/74

ETCH REV. C-P 3


SIGNATURES		DATE		digital		
DRN. 10-5-74		10-20-74				
CHK'D. [Signature]		[Signature]		TITLE VT100 ADVANCED VIDEO		
RECH. ENG. [Signature]		10-20-74				
PROJ. ENG. [Signature]		10-20-74				
PROD. [Signature]		10-20-74				
SCALE 2/1						
SHT. 1 OF 1				SIZE CODE	NUMBER	REV F
NEXT HIGHER ASSY. 3-00-5413097-0				UA5413097-0-0		

1 WO#104150

SHEET A1 OF A1

24 NOTE: FOR INDIVIDUAL FIELD SERVICE/CUSTOMER SPARES SHIPMENT USE PACKAGING INSTRUCTION A-SP-3700554-0-0.
25 NOTE: FOR BULK INTERPLANT SHIPMENT USE PACKAGING INSTRUCTIONS A-SP-3700438-00.

REVISION HISTORY			BASIC PART NO: 5413097		DRN: T. SHETRAWSKI		DATE: 10-MAR-78		D I G I T A L			
ENG	ECO NUMBER	REV	SECTION A OF A		CHK'D: T. SHETRAWSKI		DATE: 10-MAR-78		TITLE PARTS LIST			
---	INIT	A	SECTION.VARIATION INDEX		CHK'D: T. SHETRAWSKI		DATE: 10-MAR-78		VT100 ADV VIDEO			
---	5413097-ML002	C	[A] 00,01,02,03									
CJ	5413097-ML003	D	[B]									
CJ	5413097-ML004	E	[C]		DES.ENG: D. PUCCI		DATE: 10-MAR-78					
DP	5413097-ML005	F	[D]									
RB	5413097-ML006	H	[E]						DOCUMENT NUMBER			
			[F]		RESP.ENG.: D. PUCCI		DATE: 10-MAR-78					
			[H]						SIZE	CODE	NUMBER	REV
			[J]									
			[K]		MFG.ENG.: T. CORCIARI		DATE: 10-MAR-78		K	PL	5413097-0-DBP	H
			[L]									
			[M]		ASSEMBLY NUMBER:		TOP DOCUMENT NUMBER:		FILE NAME:		EDIT #	
			[N]		D-UA-5413097-0-0		B-DD-5413097-0-0		Z10B1H.PLS		9	
"THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT (C) 1981. DIGITAL EQUIPMENT CORPORATION "												



DIGITAL EQUIPMENT CORPORATION PARTS LIST					QUANTITY / VARIATION											NOTES:						
MADE BY D. HEALY DATE 14-JUN-78		CHECKED D. HEALY DATE 14-JUN-78		SECTION A1	VT100-AA	VT100-AB	VT100-NA	VT100-NB	VT100-WA	VT100-WB	VT100-WC	VT100-WD	VT100-WE	VT100-WF	VT100-WG	VT100-WH	1. VARIATIONS BA,BB,CA,CB,DA, & DB ARE SHIPPING CONFIGURATIONS ONLY. THEY ARE PACKAGED AT THE WAREHOUSE AND FA&T SYSTEMS PLANTS FOR SHIPMENT. ALL QUANTITIES ARE FOR REFERENCE ONLY.					
ENG E. WEDEKING DATE 10-JUL-78		PROD K. HOFFMAN DATE 10-JUL-78		ISSUED SECTION A2																		
ITEM NO.	DRAWING NO.	PART NO.	DESCRIPTION	REF DESIGNATION																		
1	EK-VT100-UG-001	EK-VT100-UG	GUIDE, USERS VT100	1	1	1	1	1	1	1	1	1	1	1	1							
2		3615741	LABEL, SET-UP, VT100	1	1	1	1	1	1	-	-	-	-	-	-							
3		VT100-AA	TERM., VIDEO, W/115V PLUG	1	-	-	-	-	-	-	-	-	-	-	-							
4		VT100-AB	TERM., VIDEO, W/230V PLUG	-	1	-	-	-	-	-	-	-	-	-	-							
5		VT100-NA	TERM., VIDEO, DECFORM,W/115V PLUG	-	-	1	-	-	-	-	-	-	-	-	-							
6		VT100-NB	TERM., VIDEO, DECFORM,W/230V PLUG	-	-	-	1	-	-	-	-	-	-	-	-							
7		VT100-WA	TERM., VIDEO, WORD PROCESSING, W/115V PLUG.	-	-	-	-	1	-	-	-	-	-	-	-							
8		VT100-WB	TERM., VIDEO, WORD PROCESSING, W/230V PLUG.	-	-	-	-	-	1	-	-	-	-	-	-							
9	A-SP-VT100-W-0		INSTALLATION NOTES, WORD PROCESSING TERMINAL.	-	-	-	-	1	1	1	1	1	1	1	1							
10		VT100-WC	TERM, VIDEO, FR. CANADIAN WP W/ 115V PLUG	-	-	-	-	-	-	1	-	-	-	-	-							
11		VT100-WD	TERM, VIDEO, FR. CANADIAN WP W/ 230V PLUG	-	-	-	-	-	-	-	1	-	-	-	-							
12		VT100-WE	TERM, VIDEO, FRENCH WP W/115V PLUG	-	-	-	-	-	-	-	-	1	-	-	-							
13		VT100-WF	TERM, VIDEO, FRENCH WP W/230V PLUG	-	-	-	-	-	-	-	-	-	1	-	-							
14		VT100-WG	TERM, VIDEO, DUTCH,WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	1	-							
15		VT100-WH	TERM, VIDEO, DTUCH,WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	1							
16		VT100-WJ	TERM, VIDEO, GERMAN WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-							
17		VT100-WK	TERM, VIDEO, GERMAN WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-							
18		VT100-WY	TERM, VIDEO, WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-							
E.C.O. NO. ML032 ML037 VT100- ML042 VT100- ML047				TITLE SHIPPING LIST VT100													ASSY NO. 		SIZE B	CODE PL	NUMBER VT100-0	REV. H
"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT ©1978 DIGITAL EQUIPMENT CORPORATION"				SHEET 1 OF 6													INSERTION PARTS LIST DATA BASE REV					

DRB 125

ML3

DIGITAL EQUIPMENT CORPORATION PARTS LIST					QUANTITY / VARIATION											NOTES:	
MADE BY D. HEALY DATE 14-JUN-78		CHECKED D. HEALY DATE 14-JUN-78		SECTION A2	VT100-AA	VT100-AB	VT100-NA	VT100-NB	VT100-WA	VT100-WB	VT100-WC	VT100-WD	VT100-WE	VT100-WF	VT100-WG	VT100-WH	SEE NOTE 1, PAGE 1
ENG E. WEDEKING DATE 10-JUL-78		PROD K. HOFFMAN DATE 10-JUL-78		ISSUED SECTION A2													
ITEM NO.	DRAWING NO.	PART NO.	DESCRIPTION														REF DESIGNATION
19		VT100-WZ	TERM, VIDEO, WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-	
20		3615741-01	LABFL, SET-UP, VT100 FOR SYSTEMS	-	-	-	-	-	-	1	1	1	1	1	1	1	
21		AA-H989A-TA	VT100 FOREIGN LANGUAGE SUPPLEMENT	-	-	-	-	-	-	1	1	1	1	1	1	1	
22		VT100-LA	TERM, VIDEO, W/P40 TUBE	1	-	-	-	-	-	-	-	-	-	-	-	-	
23		VT100-LB	TERM, VIDEO, W/P40 TUBE	-	1	-	-	-	-	-	-	-	-	-	-	-	
24		VT100-PA	VT100-AA EXCEPT DARK GRAY 120V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
25		VT100-PB	VT100-AB EXCEPT DARK GRAY 240V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
26		VT100-PC	VT100-PA WITHOUT ELECTRONICS 120V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
27		VT100-PD	VT100-PB WITHOUT ELECTRONICS 240V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
28		VT100-PE	VT100-PA WITHOUT ELECTRONICS & NO KEYBOARD 120V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
29		VT100-PF	VT100-PB WITHOUT ELECTRONICS & NO KEYBOARD 240V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	-	-	
30		EK-VT100-RC	VT100 PROGRAM REF CARD	1	1	1	1	1	1	1	1	1	1	1	1	1	
31		3618307-05	BOOKLET,FCC STATEMENT, WITH POUCH	1	1	1	1	1	1	1	1	1	1	1	1	1	
E.C.O. NO.																	
"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT ©1978 DIGITAL EQUIPMENT CORPORATION"				TITLE SHIPPING LIST VT100						ASSY NO. —		SIZE B	CODE PL	NUMBER VT100-0		REV. H	
										SHEET 2 OF 6		INSERTION PARTS LIST DATA BASE REV					

DIGITAL EQUIPMENT CORPORATION PARTS LIST					QUANTITY / VARIATION											NOTES:			
MADE BY D. HEALY DATE 14-JUN-78		CHECKED D. HEALY DATE 14-JUN-78		SECTION B1	VT100-WJ	VT100-WK	VT100-WY	VT100-WZ	VT100-LA	VT100-LB	VT100-PA	VT100-PB	VT100-PC	VT100-PD	VT100-PE	VT100-PF	SEE NOTE 1, PAGE 1		
ENG E. WEDEKING DATE 10-JUL-78		PROD K. HOFFMAN DATE 10-JUL-78		ISSUED SECTION B2															
ITEM NO.	DRAWING NO.	PART NO.	DESCRIPTION														REF DESIGNATION		
1	EK-VT100-UG-001	EK-VT100-UG	GUIDE, USERS VT100	1	1	1	1	1	1	-	-	-	-	-	-	-			
2		3615741	LABEL, SETUP, VT100	-	-	-	-	1	1	-	-	-	-	-	-	-			
3		VT100-AA	TERM., VIDEO, W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
4		VT100-AB	TERM., VIDEO, W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
5		VT100-NA	TERM., VIDEO, DECFORM, W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
6		VT100-NB	TERM., VIDEO, DECFORM, W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
7		VT100-WA	TERM., VIDEO, WORD PROCESSING W/115V PLUG.	-	-	1	-	-	-	-	-	-	-	-	-	-			
8		VT100-WB	TERM., VIDEO, WORD PROCESSING, W/230V PLUG.	-	-	-	1	-	-	-	-	-	-	-	-	-			
9	A-SP-VT100-W-0		INSTALLATION NOTES, WORD PROCESSING TERMINAL.	1	1	1	1	-	-	-	-	-	-	-	-	-			
10		VT100-WC	TERM, VIDEO, FR. CANADIAN WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
11		VT100-WD	TERM, VIDEO, FR. CANADIAN WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
12		VT100-WE	TERM, VIDEO, FRENCH WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
13		VT100-WF	TERM, VIDEO, FRENCH WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
14		VT100-WG	TERM, VIDEO, DUTCH WP W/115V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
15		VT100-WH	TERM, VIDEO, DUTCH WP W/230V PLUG	-	-	-	-	-	-	-	-	-	-	-	-	-			
16		VT100-WJ	TERM, VIDEO, GERMAN WP W/115V PLUG	1	-	-	-	-	-	-	-	-	-	-	-	-			
17		VT100-WK	TERM, VIDEO, GERMAN WP W/230V PLUG	-	1	-	-	-	-	-	-	-	-	-	-	-			
18		VT100-WY	TERM, VIDEO, WP W/115V PLUG	-	-	1	-	-	-	-	-	-	-	-	-	-			
E.C.O. NO.																			
"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1978 DIGITAL EQUIPMENT CORPORATION"				TITLE SHIPPING LIST VT100				ASSY NO. —				SIZE B		CODE PL		NUMBER VT100-0		REV. H	
								SHEET 3				OF 6		INSERTION PARTS LIST DATA BASE REV					

DIGITAL EQUIPMENT CORPORATION PARTS LIST				QUANTITY / VARIATION											NOTES: SEE NOTE 1, PAGE 1					
MADE BY DATE		D. HEALY 14-JUN-78		CHECKED DATE		D. HEALY 14-JUN-78		SECTION B2												
ENG DATE		E. WEDEKING 10-JUL-78		PROD DATE		K. HOFFMAN 10-JUL-78		ISSUED SECTION B2												
ITEM NO.	DRAWING NO.	PART NO.	DESCRIPTION	VT100-WJ	VT100-WK	VT100-WY	VT100-WZ	VT100-LA	VT100-LB	VT100-PA	VT100-PB	VT100-PC	VT100-PD	VT100-PE	VT100-PF	REF DESIGNATION				
19		VT100-WZ	TERM, VIDEO, WP W/230V PLUG	-	-	-	1	-	-	-	-	-	-	-	-					
20		3615741-01	LABEL, SET-UP, VT100 FOR SYSTEMS	1	1	1	1	-	-	-	-	-	-	-	-					
21		AA-H989A-TA	VT100 FOREIGN LANGUAGE SUPPLEMENT	1	1	1	1	-	-	-	-	-	-	-	-					
22		VT100-LA	TERM, VIDEO, W/P40 TUBE	-	-	-	-	1	-	-	-	-	-	-	-					
23		VT100-LB	TERM, VIDEO, W/P40 TUBE	-	-	-	-	-	1	-	-	-	-	-	-					
24		VT100-PA	VT100-AA EXCEPT DRAK GRAY 120V PRIVATE BRAND	-	-	-	-	-	-	1	-	-	-	-	-					
25		VT100-PB	VT100-AB EXCEPT DARK GRAY 240V PRIVATE BRAND	-	-	-	-	-	-	-	1	-	-	-	-					
26		VT100-PC	VT100-PA WITHOUT ELECTRONICS 120V PRIVATE BRAND	-	-	-	-	-	-	-	-	1	-	-	-					
27		VT100-PD	VT100-PB WITHOUT ELECTRONICS 240V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	1	-	-					
28		VT100-PE	VT100-PA WITHOUT ELECTRONICS & NO KEYBOARD 120V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	1	-					
29		VT100-PF	VT100-PB WITHOUT ELECTRONICS & NO KEYBOARD 240V PRIVATE BRAND	-	-	-	-	-	-	-	-	-	-	-	1					
30		EK-VT100-RC	VT100 PROGRAM REF CARD	1	1	1	1	1	1	1	1	1	1	1	1					
31		3618307-05	BOOKLET, FCC STATEMENT, WITH POUCH	1	1	1	1	1	1	1	1	-	1	1	1					
E.C.O. NO.																				
THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT ©1978 DIGITAL EQUIPMENT CORPORATION				TITLE SHIPPING LIST VT100				ASSY NO. #				SIZE B		CODE PL		NUMBER VT100-0		REV. H		
DRB 125				SHEET 4 OF 6				INSERTION PARTS LIST DATA BASE REV												

1713

digital PARTS LIST				QUANTITY / VARIATION												NOTES:																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																														
DRN. D. HEALY DATE 14-JUN-78		DES. ENG. E. WEDEKING DATE 10-JUL-78		MFG. ENG. K. HOFFMAN DATE 10-JUL-78		VT100-BA	VT100-BB	VT100-CA	VT100-CB	VT100-DA	VT100-DB																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																			

digital PARTS LIST				QUANTITY / VARIATION										NOTES: SEE NOTE1, PAGE 1					
DRN. D. HEALY DATE 14-JUN-78		DES. ENG. E. WEDEKING DATE 10-JUL-78		MFG. ENG. K. HOFFMAN DATE 10-JUL-78		VT100-BA	VT100-BB	VT100-CA	VT100-CB	VT100-DA	VT100-DB								
CHK'D. D. HEALY DATE 14-JUN-78		RESP. ENG. E. WEDEKING DATE 10-JUL-78		NEXT HIGHER DOC. B-DD-VT100-0															
ITEM NO.	DRAWING NO.	PART NO.	DESCRIPTION																REFERENCE DESIGNATORS
19		VT100-WZ	TERM, VIDEO, WP W/230V PLUG	-	-	-	-	-	-	-	-								
20		3615741-01	LABEL, SET-UP, VT100 FOR SYSTEMS	-	-	-	-	-	-	-	-								
21		AA-H989A-TA	VT100 FOREIGN LANGUAGE SUPPLEMENT	-	-	-	-	-	-	-	-								
22		VT100-LA	TERM, VIDEO, W/P40 TUBE	-	-	-	-	-	-	-	-								
23		VT100-LB	TERM, VIDEO, W/P40 TUBE	-	-	-	-	-	-	-	-								
24		VT100-PA	VT100-AA EXCEPT DARK GRAY 120V PRIVATE BRAND	-	-	-	-	-	-	-	-								
25		VT100-PB	VT100-AB EXCEPT DARK GRAY 240V PRIVATE BRAND	-	-	-	-	-	-	-	-								
26		VT100-PC	VT100-PA WITHOUT ELECTRONICS 120V PRIVATE BRAND	-	-	-	-	-	-	-	-								
27		VT100-PD	VT100-PB WITHOUT ELECTRONICS 240V PRIVATE BRAND	-	-	-	-	-	-	-	-								
28		VT100-PE	VT100-PA WITHOUT ELECTRONICS & NO KEYBOARD 120V PRIVATE BRAND	-	-	-	-	-	-	-	-								
29		VT100-PF	VT100-PB WITHOUT ELECTRONICS & NO KEYBOARD 240V PRIVATE BRAND	-	-	-	-	-	-	-	-								
30		EK-VT100-RC	VT100 PROGRAM REF CARD	-	-	-	-	-	-	-	-								
31		3618307-05	BOOKLET, FCC STATEMENT, WITH POUCH	-	-	-	-	-	-	-	-								
ECO NO.																			
"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1978 DIGITAL EQUIPMENT CORPORATION"				TITLE SHIPPING LIST VT100				ASSY. NO. //				SIZE B	CODE PL	NUMBER VT100-0		REV. H			
								SECTION C2 OF C2						SHEET 6 OF 6					

DIGITAL EQUIPMENT CORPORATION
MAYNARD, MASSACHUSETTS

ENGINEERING SPECIFICATION

DATE 6/28/79

VT100-W Word Processing Terminals

Installation Notes

REV	DESCRIPTION	CHG NO	ORIG	DATE	APPD BY	DATE
A	ECO CHANGE	VT100-W-TREMBLAY ML028		3/12/79	W. Tremblay	6/1/80

The VT100 family of Word Processing Terminals consists of the basic VT100 terminal assembly to which one or more optional modules are substituted to make unique terminals, dedicated to word processing applications in various languages.

Table 1 lists the unique parts make-up of the various VT100 Word Processing Terminals.

The VT100 incorporates a user set-up option which is activated by the set-up key on the keyboard. To maintain order among DEC Word Processing Systems using the VT100, a WORD PROCESSING STANDARD SET-UP has been defined. These settings are preset at the factory.

Table 2 shows the correct set-up B settings for VT100-WA and VT100-WC through VT100-WF, VT100-WH, and VT100-WJ.

Verify that the terminal is set-up correctly. If necessary, change incorrect settings then store the settings in the VT100's semi-permanent memory (Ref: VT100 User Guide EK-VT100-001).

Unique to the VT100 Word Processing Terminal is a Word Processing Advanced Video Module P/N 5413097-X. Table 3 illustrates ROM and jumper placement for the various modules.

Also unique to the VT100 Foreign Word Processing Terminals is a Word Processing Advanced Video Module P/N 5413097-Y. Table 4 illustrates ROM and jumper placement for the various modules.

Table 5 explains how to use the set-up C mode to select any one of 5 different languages.

Table 1

Word Processing VT100 Unique Parts

Variation	Basic Unit	Unique Part	Part Number
VT100-WA	French Canadian Key Bd.	French Canadian Key Bd.	7015765-05
VT100-WB	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WC	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WD	Port. Language Advanced	Port. Language Advanced	7015765-06
VT100-WE	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WF	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WG	Video Module w/ROM A	Basic Video Board	7015765-07
VT100-WH	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WJ	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WK	Port. Language Advanced	Port. Language Advanced	7015765-08
VT100-WL	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WM	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WN	Video Module w/ROM A	Basic Video Board	7015765-09
VT100-WO	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WP	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WQ	Port. Language Advanced	Port. Language Advanced	7015765-10
VT100-WR	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WS	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WT	Video Module w/ROM A	Basic Video Board	7015765-11
VT100-WU	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WV	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WW	Port. Language Advanced	Port. Language Advanced	7015765-12
VT100-WX	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WY	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WZ	Video Module w/ROM A	Basic Video Board	7015765-13

Table 2

Word Processing User Option Set-up "B"

SET-UP B	TO EXIT PRESS "SET-UP"
1100 0101 0000 0010	T SPEED 9600 R SPEED 9600

Table 3

Word Processing User Option Set-up "B"

SET-UP B	TO EXIT PRESS "SET-UP"
1100 0101 1000 0011	T SPEED 9600 R SPEED 9600

This document contains confidential proprietary information of DEC. This information shall not be disclosed to persons outside the design, production or manufacturing of DEC products. It is to be used for design, production or manufacturing of DEC products only. It is to be controlled by DEC. It is to be controlled by DEC. It is to be controlled by DEC.

Table 2
Word Processing User Option Set-up "B"

VT100-WA Set-up B

SET-UP B

TO EXIT PRESS "SET-UP"

1100 0101 0000 0010

T SPEED 9600 R SPEED 9600

SET-UP B mode may only be entered from SET-UP A mode. To enter SET-UP B from SET-UP A, press the 5 key on the main keyboard. The display will have a presentation similar to the figure shown above.

The table shown below explains the function of each bit and their proper setting.




Table 1 (continued)
Word Processing VT100 Unique Parts

Variation	Basic Unit	Unique Part	Part Number
VT100-WD	French Canadian Key Bd.	French Canadian Key Bd.	7015765-05
VT100-WE	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WF	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WG	Port. Language Advanced	Port. Language Advanced	7015765-06
VT100-WH	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WJ	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WK	Video Module w/ROM A	Basic Video Board	7015765-07
VT100-WL	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WM	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WN	Port. Language Advanced	Port. Language Advanced	7015765-08
VT100-WO	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WP	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WQ	Video Module w/ROM A	Basic Video Board	7015765-09
VT100-WR	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WS	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WT	Port. Language Advanced	Port. Language Advanced	7015765-10
VT100-WU	Video Module w/ROM A	Basic Video Board	5413097-03
VT100-WV	Port. Language Advanced	Port. Language Advanced	5413009-02
VT100-WW	Video Module w/ROM A	Basic Video Board	7015765-11
VT100-WX	Port. Language Advanced	Port. Language Advanced	5413097-03
VT100-WY	Video Module w/ROM A	Basic Video Board	5413009-02
VT100-WZ	Port. Language Advanced	Port. Language Advanced	7015765-12

Table 2
Word Processing User Option Set-up "B"

VT100-WB Set-up B

SET-UP B

TO EXIT PRESS "SET-UP"

1100 0101 1000 0011

T SPEED 9600 R SPEED 9600

SET-UP B mode may only be entered from SET-UP A mode. To enter SET-UP B from SET-UP A, press the 5 key on the main keyboard. The display will have a presentation similar to the figure shown above.

The table shown below explains the function of each bit and their proper setting.




Table 3
Word Processing User Option Set-up "B"
VT100-WC-WK, WY, and WZ Set-up B

SET-UP B
TO EXIT PRESS "SET-UP"

1100 0101 0000 0001 P=80 T 9600 R 9600

NOTE: For WC and WD variations Group 4 should contain all zero's, unless 50 Hz, local echo and/or parity check is desired.
SET-UP B mode may only be entered from SET-UP A mode. To enter SET-UP B from SET-UP A, press the 5 key on the main keyboard. The display will have a presentation similar to the figure shown above.

The table shown below explains the function of each bit and their proper setting.

If the parity setting (P=?) is incorrect, it can be changed by holding the shift key down and pressing the P key repeatedly until the desired setting is displayed.




Table 5
Word Processing Adv. Video Module
ROM and Jumper Locations

VT100-WA & WB 5413097-01




Table 4
Word Processing User Option Set-up C

The SET-up C mode for VT100 variations -WC through WK, -WY and -WZ allows you to select any one of the following languages.

French Canadian
French
Dutch
German
English

SET-UP C mode may only be entered from SET-UP A mode. To enter SET-UP C from SET-UP A, press the 5 key on the main keyboard twice. The display will have a presentation similar to the figure shown below.

SET-UP C
TO EXIT PRESS "SET-UP"

DISPLAY ENGLISH KEYBOARD ENGLISH


To change the language setting for the display and/or keyboard, advance the cursor until it is positioned above the incorrect language setting then press the number 6 key repeatedly until the desired language setting is displayed.

For terminals set-up for French all numbers (0-9) on the main keyboard are in the shifted position, therefore, they can only be accessed by holding the shift key down and then pressing the desired number key.

It is suggested that the "Caps Lock" key ("Shift Lock" in the French keyboard mode) be always engaged when doing set-up functions to eliminate confusion during set-up.



Table 5 (continued)
Word Processing Adv. Video Module
ROM and Jumper Locations

VT100-WC-WK, WY & WZ 5413097-03



THIS DRAWING AND SPECIFICATIONS, MANUAL, AND THE PROPERTY OF BETHLE EMERYMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE CONSTRUCTION OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.

COPYRIGHT © BETHLE EMERYMENT CORPORATION



LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION		REFERENCE DESIGNATOR
					00	01	
1	1	E-MD-5014130-0-0	5014130-00	DRILLED AND ETCH BOARD FOR VT100	1	1	
2	2		1016544-00	.1 MFD 100V 10% MYLR	2	2	C107,C442
3	3		1016546-00	.22 MFD 660V 10% MET. MYLR	1	1	C449
4	4		1016569-00	.0022 MFD 100V 10% MYLR	2	2	C436,C402
5	5		1016639-00	.01 MFD 200V 10% MYLR	1	1	C320
6	6		1016547-00	.022 MFD 200V 10% MYLR	1	1	C438
7	7		1016548-00	1000 MFD 16V +50-10% AL EL	1	1	C321
8	8		1010274-02	1 MFD 50V +80-20% CER	1	1	C443
9	9		1016555-00	22 MFD 50V +50-10% AL EL	2	2	C102,C103
10	10		1016496-00	4.7MFD 35V 20% S.TANT	2	2	C318,C319
11	11		1016554-00	75 MFD 6V +75-10% AL EL	1	1	C439
12	12		1016553-00	4.7MFD 25V +75-10% AL EL	2	2	C312,C437
13	13		1016558-00	10 MFD 25V 20% AL EL	1	1	C441
14	14		1016557-00	470 MFD 16V +50-10% AL EL	3	3	C106,C434,C440
15	15		1016556-00	.05 MFD 100V +80-20%Z5U DISC	3	3	C213,C314,C404
16	16		1016570-00	.001 MFD 500V +80-20%Z5U DISC	2	2	C435,C403
17	17		1016571-00	.02 MFD 500V +80-20%Z5U DISC	4	4	C104,C105,C486,C487
18	18		1016572-00	300.0 MMF 500V 10% X5P DISC	1	1	C101
19	19		1000004-00	.02 MFD 100V 20% Z5U DISC	4	4	C322,C323,C324,C325
20	20		1116474-00	1N 4007 PIV=1000 I=1A D041	4	4	CR101,CR102,CR103,CR104
21	21		1116477-00	1N 4156 PIV= 20 D035	1	1	CR304
22	22		1114892-00	1N 4747A VZ= 20.0 5% 1W	1	1	CR410
23	23		1116476-00	PIV=400	1	1	CR408
24	24		1216530-04	MAGNET,PINCUSHION 10 GAUSS	1	1	
25	25	SEE NOTE	1003053-00	.047 MFD 250V 20% MET. MYLR	1	1	C316
26	26		1316522-00	2.50 K .25 W20.0 % POT	1	1	R342
27	27		1316522-02	5.0 M .25 W20.0 % POT	1	1	R477
28	28		1316522-01	100.0 K .25 W20.0 % POT	1	1	R109
29	29		1317528-00	39.0 2.0 W10.0 % CC	1	1	R470
30	30		1300479-00	10.0 K .25 W 5.0 % CF	1	1	R291

REVISION HISTORY			BASIC PART NO: 5414131			DRN: KENT GLEEZEN			DATE: 24-MAR-81			D I G I T A L		
ENG	ECO NUMBER	REV	SECTION A OF A			CHK'D: KENT GLEEZEN			DATE: 24-MAR-81			TITLE PARTS LIST		
---	INITIAL	P	SECTION VARIATION INDEX			DES.ENG: DICK PUCCI			DATE: 24-MAR-81			VT100 MONITOR		
DP	5414131-ML007	R	[A] 00,01			RESP.ENG.: DICK PUCCI			DATE: 24-MAR-81			DOCUMENT NUMBER		
DP	5414131-ML008	S	[B]			MFG.ENG.: AL JOHNS			DATE: 24-MAR-81			SIZE CODE NUMBER REV		
CT	5414131-ML010	T	[C]			ASSEMBLY NUMBER:			TOP DOCUMENT NUMBER:			FILE NAME: EDIT #		
WB	5414131-ML011	U	[D]			D-UA-5414131-0-0			B-DD-5414131-0-0			Z2387U,PLS 15		
			[E]											
			[F]											
			[H]											
			[J]											
			[K]											
			[L]											
			[M]											
			[N]											
*THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT (C) 1982. DIGITAL EQUIPMENT CORPORATION *														

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION		REFERENCE DESIGNATOR
					00	01	
31	31		1300445-00	4.70 K .50 W 5.0 % CF	1	1	R331
32	32		1316504-00	68.0 K .50 W 5.0 % CF	1	1	R332
33	33		1300385-00	1.20 K .50 W 5.0 % CF	1	1	R344
34	34		1316506-00	100.0 K .50 W 5.0 % CF	2	2	R472,R473
35	35		1316508-00	5.60 K .50 W 5.0 % CF	1	1	R338
36	36		1316509-00	*** THIS ITEM IS NOT USED ***	-	-	
37	37		1302396-00	150.0 K .25 W 5.0 % CF	1	1	R106
38	38		1300228-00	100.0 .50 W 5.0 % CF	2	2	R481,R343
39	39		1300364-00	1.0 K .50 W 5.0 % CF	1	1	R468
40	40		1300296-00	330.0 .50 W 5.0 % CF	1	1	R345
41	41		1300356-00	820.0 .50 W10.0 % CF	1	1	R108
42	42		1300461-00	6.80 K .50 W 5.0 % CF	1	1	R339
43	43		1300440-00	3.30 K .50 W 5.0 % CF	1	1	R110
44	44		1300496-00	15.0 K .25 W 5.0 % CF	1	1	R107
45	45		1300274-00	220.0 .50 W 5.0 % CF	1	1	R105
46	46		1300285-00	*** THIS ITEM IS NOT USED ***	-	-	
47	47		1316525-00	1.0 3.0 W10.0 % WW	1	1	R478
48	48		1509525-00	2N 3906 FNP 310MW SI 40100 Y	1	-	Q298
			CONT		-	2	Q298,Q100
49	49		1516492-00	2N 5830 NPN 1W SI100 1	1	1	Q101
50	50		1509524-00	2N 3904 NPN 310MW SI 40 40 M	2	2	Q308,Q401
51	51		1516491-00	2N 6427 NPN 1.5W SI 40 1.5	1	1	Q309
52	52		1516532-00	NPN 125W SI250 25	1	1	Q310
53	53		1516490-00	MPSU05 NPN 10W SI	1	1	Q413
54	54		1517534-00	BU 407D NPN POWER TRANS T0220	1	1	Q414
55	55		4901303-00	WAX	A/R	A/R	
56	56		9107685-00	TUBING,SHRINK .500ID EXP	A/R	A/R	
57	57		1616309-00	XFMR,HORIZONTAL DRIVE	1	1	T403
58	58		1616538-00	COIL,HORIZONTAL,LINEAR	1	1	L402
59	59		1616536-00	XFMR HORIZONTAL WIDTH	1	1	L403
60	60		1210929-05	FUSE, SUB-MINI, 2.500A, 125V, A	1	1	F401
61	61		1216521-01	PCB,HEADER 08PIN(1X08).156CC STR	1	1	S102
62	62		1216521-00	PCB,HEADER 04PIN(1X04).156CC STR	1	1	S103
63	63		1216471-00	HEAT SINKS,TO-3/TO-66 1.531X1.25	1	1	
64	64		1217561-00	HEAT SINKS,TO-220 1.390X1.00	1	1	
65	65		4901304-00	COMPOUND, SILICONE THERMAL, VISC	A/R	A/R	
66	66		9006022-01	*** THIS ITEM IS NOT USED ***	-	-	
67	67		1001776-00	1 MFD 35V 10% S.TANT	1	1	C315
68	68		1304837-00	*** THIS ITEM IS NOT USED ***	-	-	
69	69		1300315-00	470.0 .50 W 5.0 % CF	1	1	R401
70	70		1300415-00	2.20 K .50 W 5.0 % CF	2	2	R402,R403
71	71		1300443-00	3.90 K .50 W 5.0 % CF	1	1	R404
72	72		1300467-00	7.50 K .50 W 5.0 % CF	1	1	R405
73	73		1000042-00	1000.0 MMF 100V 5%200PPM MICA	1	1	C401
74	74		1911944-00	555CN TIMER,FUNCT.BLOCK	1	1	E1
75	75		9006659-00	WASHER,FLAT STEEL	2	2	
76	76		9008185-00	NUT,HEX EXT TOOTH LCKWSHR 6-32	3	3	
77	77		1300197-00	33.0 .25 W 5.0 % CF	1	1	R471

! D ! I ! G ! I ! T ! A ! L !	! TITLE	! SECTION A OF A	! SIZE ! CODE !	! DOCUMENT NUMBER	! REV !
! ! ! ! ! ! ! !	! VT100 MONITOR	! ! ! ! ! ! ! !	! K ! PL !	! 5414131-0-DBP	! U !
! ! ! ! ! ! ! !	! ! ! ! ! ! ! !	! ! ! ! ! ! ! !	! ! ! ! ! ! ! !	! ! ! ! ! ! ! !	! ! ! ! ! ! ! !

LINE	ITEM	DOCUMENT NUMBER	PART NUMBER	DESCRIPTION	QTY PER VARIATION		REFERENCE DESIGNATOR
					00	01	
78	78		1300432-00	3.0 K .25 W 5.0 % CF	1	1	R400
79	79		1300439-00	3.30 K .25 W 5.0 % CF	1	1	R104
80	80		1301775-00	820.0 .25 W 5.0 % CF	1	1	R293
81	81		1300295-00	330.0 .25 W 5.0 % CF	1	1	R294
82	82		9107776-99	WIRE(WRAP) 22AWG IPVC UL14	A/R	-	
83	83		9009185-00	JUMPER, WIRE, INSULATED, BLACK B	1	1	W1
84	84		1302602-00	56.0 .25 W 5.0 % CF	2	-	R102,R103
			CONT		-	1	R103
85	85		1300250-00	150.0 .25 W 5.0 % CF	-	1	R102
86	86		1300316-00	470.0 .25 W 5.0 % CF	-	1	R111
87	87		1302395-00	56.0 K .25 W 5.0 % CF	-	1	R112
88	88		1302092-00	220.0 K .25 W 5.0 % CF	1	1	R113
89	89		1312930-00	5.10 K .25 W 5.0 % CF	1	-	R292
			CONT		-	3	R292,R114,R115
90	90		1001610-00	.01 MFD 50V +80-20% Z5U CER	-	1	C108
91	91		1116475-00	1N 4148 PIV= 75 D035	2	-	CR302,CR303
			CONT		-	3	CR302,CR303,CR100
92	92		1111854-01	MR 817 PIV=800 I= 1A D041 S	1	1	CR409
93	93		9006023-01	SCREW,MACH PAN PHIL 6-	2	2	
94	94		1316522-06	25.0 K .25 W20.0 % POT	1	1	R334
95	95		1301327-00	68.0 K .25 W 5.0 % CF	1	1	R335
96	96		1319255-06	12.0 1.0 W 5.0 % M.OXIDE	1	1	R337
97	97		1301732-00	620.0 .50 W 5.0 % CF	1	1	R341
98	98		1309785-00	300.0 2.0 % NTC THERM	1	1	R346
99	99		1300478-00	10.0 K .50 W 5.0 % CF	1	1	R333

100 NOTE: P/N 1000051-00 CAN BE USED AS AN ALTERNATE FOR P/N 1003053-00.

D I G I T A L				TITLE		SECTION A OF A		SIZE	CODE	DOCUMENT NUMBER	REV
				VT100 MONITOR				K	PL	5414131-0-DBP	U

